

A deconvolution approach to estimation of a common shape in a shifted curves model

Jeremie Bigot and Sebastien Gadat

Institut de Mathématiques de Toulouse
Université de Toulouse et CNRS (UMR 5219)
31062 Toulouse, Cedex 9, France

Jeremie.Bigot@math.univ-toulouse.fr, Sebastien.Gadat@math.univ-toulouse.fr

April 2009

Abstract

This paper considers the problem of adaptive estimation of a mean pattern in a randomly shifted curve model. We show that this problem can be transformed into a linear inverse problem, where the density of the random shifts plays the role of a convolution operator. An adaptive estimator of the mean pattern, based on wavelet thresholding is proposed. We study its consistency for the quadratic risk as the number of observed curves tends to infinity, and this estimator is shown to achieve a near-minimax rate of convergence over a large class of Besov balls. This rate depends both on the smoothness of the common shape of the curves and on the decay of the Fourier coefficients of the density of the random shifts. Hence, this paper makes a connection between mean pattern estimation and the statistical analysis of linear inverse problems, which is a new point of view on curve registration and image warping problems. Some numerical experiments are given to illustrate the performances of our approach and to compare them with another algorithm existing in the literature.

Keywords: Mean pattern estimation, Curve registration, Inverse problem, Deconvolution, Meyer wavelets, Adaptive estimation, Besov space, Minimax rate.

AMS classifications: Primary 62G08; secondary 42C40

1 Introduction

1.1 Model and objectives

Assume that we observe realizations of n noisy and randomly shifted curves $Y_1, \dots, Y_n$ coming from the following Gaussian white noise model

$$dY_m(x) = f(x - \tau_m)dx + \epsilon_m dW_m(x), \quad x \in [0, 1], \quad m = 1, \dots, n \quad (1.1)$$

where f is the unknown mean pattern (also called common shape) of the curves, W_m are independent standard Brownian motions on $[0, 1]$, the ϵ_m 's represent levels of noise which may vary from curve to curve, and the τ_m 's are unknown random shifts independent of the W_m 's. The aim of this paper is to study some statistical aspects related to the problem of estimating f .

This model is realistic in many situations where it is reasonable to assume that the observed curves represent replications of almost the same process and when a large source of variation in the experiments is due to transformations of the time axis. Such a model is commonly used in many applied areas dealing with functional data such as neuroscience [16] or biology [31]. More generally, the model (1.1) represents a kind of benchmark model for studying the difficult problem of recovering a mean pattern from a set of similar curves or images in the presence of random deformations and additive noise, which corresponds to the general setting of Grenander's theory

of shapes [13]. The results derived in this paper show that the model (1.1), although simple, already provides some new insights on the statistical aspects of mean pattern estimation which is a problem frequently encountered in image warping, see [12] and the discussion therein for an overview.

The function $f : \mathbb{R} \rightarrow \mathbb{R}$ is assumed to be periodic with period 1, and the shifts τ_m are supposed to be independent and identically distributed (iid) random variables with density $g : \mathbb{R} \rightarrow \mathbb{R}^+$ with respect to the Lebesgue measure dx on $\mathbb{R}$. Our goal is to estimate non-parametrically the shape function f on $[0, 1]$ as the number of curves n goes to infinity.

Let $L^2([0, 1])$ be the space of squared integrable functions on $[0, 1]$ with respect to dx , and denote by $\|f\|^2 = \int_0^1 |f(x)|^2 dx$ the squared norm of a function f . Assume that $\mathcal{F} \subset L^2([0, 1])$ represents some smoothness class of functions (e.g a Sobolev or a Besov ball), and let $\hat{f}_n \in L^2([0, 1])$ be some estimator of the common shape f , i.e a measurable function of the random processes Y_m , $m = 1, \dots, n$. For some $f \in \mathcal{F}$, the risk of the estimator $\hat{f}_n$ is defined to be

$$\mathcal{R}(\hat{f}_n, f) = \mathbb{E} \|\hat{f}_n - f\|^2$$

where the above expectation $\mathbb{E}$ is taken with respect to the law of $\{Y_m, m = 1, \dots, n\}$. In this paper, we propose to investigate the optimality of an estimator by introducing the following minimax risk

$$\mathcal{R}_n(\mathcal{F}) = \inf_{\hat{f}_n} \sup_{f \in \mathcal{F}} \mathcal{R}(\hat{f}_n, f),$$

where the above infimum is taken over the set of all possible estimators in model (1.1). One of the main contributions of this paper is to derive asymptotic lower and upper bounds for $\mathcal{R}_n(\mathcal{F})$ which, to the best of our knowledge, has not been considered before.

Indeed, we show that there exists constants M_1, M_2 , a sequence of reals $r_n = r_n(\mathcal{F})$ tending to infinity, and an estimator $\hat{f}_n^*$ such that

$$\lim_{n \rightarrow +\infty} r_n \mathcal{R}_n(\mathcal{F}) \geq M_1 \text{ and } \lim_{n \rightarrow +\infty} r_n \sup_{f \in \mathcal{F}} \mathcal{R}(\hat{f}_n^*, f) \leq M_2.$$

However, the construction of $\hat{f}_n^*$ may depend on unknown quantities such as the smoothness of f , and such estimates are therefore called non-adaptive. Since it is now recognized that wavelet decomposition is a powerful tool to derive adaptive estimators, see e.g [9], a second contribution of this paper is thus to propose wavelet-based estimators $\hat{f}_n$ that attain a near-minimax rate of convergence in the sense there exists a constant M_2 such that

$$\lim_{n \rightarrow +\infty} (\log n)^{-\beta} r_n \sup_{f \in \mathcal{F}} \mathcal{R}(\hat{f}_n, f) \leq M_2, \text{ for some } \beta > 0.$$

1.2 Main result

Minimax risks will be derived under particular smoothness assumptions on the density g . The main result of this paper is that the difficulty of estimating f is quantified by the decay to zero of the Fourier coefficients γ_ℓ of the density g of the shifts defined as

$$\gamma_\ell = \mathbb{E} \left(e^{-i2\pi\ell\tau} \right) = \int_{-\infty}^{+\infty} e^{-i2\pi\ell x} g(x) dx, \quad (1.2)$$

for $\ell \in \mathbb{Z}$. Depending how fast these Fourier coefficients tend to zero as $|\ell| \rightarrow +\infty$, the reconstruction of f will be more or less accurate. This comes from the fact that the expected value of each observed process $Y_m(x)$ is given by

$$\mathbb{E} Y_m(x) = \mathbb{E} f(x - \tau_m) = \int_{-\infty}^{+\infty} f(x - \tau) g(\tau) d\tau, \text{ for } x \in [0, 1].$$

This expected value is thus the convolution of f by the density g which makes the problem of estimating f an inverse problem whose degree of ill-posedness and associated minimax risk depend on the smoothness assumptions on g .

This phenomenon is a well-known fact in deconvolution problems, see e.g [17] [27], [28], and more generally for linear inverse problems as studied in [6]. In this paper, the following type of assumption on g is considered:

Assumption 1.1 *The Fourier coefficients of g have a polynomial decay i.e. for some real $\nu > 0$, there exist two constants $C_{\max} \geq C_{\min} > 0$ such that $C_{\min}|\ell|^{-\nu} \leq |\gamma_\ell| \leq C_{\max}|\ell|^{-\nu}$ for all $\ell \in \mathbb{Z}$.*

In standard inverse problems such as deconvolution, the optimal rate of convergence we can expect from an arbitrary estimator typically depends on such smoothness assumptions. The parameter ν is usually referred to as the degree of ill-posedness of the inverse problem, and it quantifies the difficulty of inverting the convolution operator. The following theorem shows that a similar phenomenon holds for the minimax risk associated to model (1.1). Note that to simplify the presentation, all the theoretical results are given for the simple setting where the level of noise is the same for all curves i.e. $\epsilon_m = \epsilon$ for all $m = 1, \dots, n$ and some $\epsilon > 0$.

Theorem 1.1 *Suppose that the smoothness class $\mathcal{F}$ is a Besov ball $B_{p,q}^s(A)$ of radius $A > 0$ with $p, q \geq 1$ and smoothness parameter $s > 0$ (a precise definition of Besov spaces will be given later on). Suppose that g satisfies Assumption 1.1, and is such that there exist two constants $C > 0$ and $\alpha > 1$ satisfying $g(x) \leq \frac{C}{1+|x|^\alpha}$ for all $x \in \mathbb{R}$. Let $p' = \min(2, p)$ and assume that $s \geq 1/p'$. If $s > 2\nu + 1$, then*

$$r_n(\mathcal{F}) = n^{\frac{2s}{2s+2\nu+1}}.$$

Hence, Theorem 1.1 shows that under Assumption 1.1 the minimax rate r_n is of polynomial order of the sample size n , and that this rate deteriorates as the degree of ill-posedness ν increases. Such a behavior is well known for standard periodic deconvolution in the white noise model [17], [27], and Theorem 1.1 shows that a similar phenomenon holds for the model (1.1). To the best of our knowledge, this is a new result which makes a connection between mean pattern estimation and the statistical analysis of deconvolution problems.

1.3 Fourier Analysis and an inverse problem formulation

Let us first remark that the model (1.1) exhibit some similarities with periodic deconvolution in the white noise model as described in [17]. For $x \in [0, 1]$, let us define the following density function

$$G(x) = \sum_{k \in \mathbb{Z}} g(x + k). \quad (1.3)$$

Note that $G(x)$ exists for all $x \in [0, 1]$ provided g has a sufficiently fast decay at infinity. In particular, the condition that $g(x) \leq \frac{C}{1+|x|^\alpha}$ for all $x \in \mathbb{R}$ and some $\alpha > 1$ (see Assumption 3.1 below) is sufficient to guarantee the existence of G . Since f is periodic with period 1, one has

$$\int_{-\infty}^{+\infty} f(x - \tau)g(\tau)d\tau = \int_0^1 f(x - \tau)G(\tau)d\tau,$$

and note that $\gamma_\ell = \int_{-\infty}^{+\infty} e^{-i2\pi\ell x}g(x)dx = \int_0^1 e^{-i2\pi\ell x}G(x)dx$. Hence, if one defines $\xi_m(x) = f(x - \tau_m) - \int_0^1 f(x - \tau)G(\tau)d\tau$ and $\xi(x) = \frac{1}{n} \sum_{m=1}^n \xi_m(x)$, then taking the mean of the n equations in (1.1) yields the model

$$dY(x) = \int_0^1 f(x - \tau)G(\tau)d\tau dx + \xi(x)dx + \frac{\epsilon}{\sqrt{n}}dW(x), \quad x \in [0, 1], \quad (1.4)$$

with $\epsilon^2 = \frac{1}{n} \sum_{m=1}^n \epsilon_m^2$ and where $W(x)$ is a standard Brownian motion [0, 1].

The model (1.4) differs from the periodic deconvolution model investigated in [17] by the error term $\xi(x)$. Asymptotically $\xi(x)$ is a Gaussian variable, so this suggests to use the wavelet thresholding procedures developed in [17] to derive upper bounds for the minimax risk. However, it should be noted that the additive error term $\xi(x)$ significantly complicates the estimation procedure as *the variance of $\xi(x)$ clearly depends on the unknown function f and must therefore be estimated*. Moreover, deriving lower bounds for the minimax risk in models such as (1.4) is significantly more difficult than in the standard white noise model without the additive term $\xi(x)$.

Now let us formulate models (1.1) and (1.4) in the Fourier domain. Supposing that $f \in L^2([0, 1])$, we denote by θ_ℓ its Fourier coefficients for $\ell \in \mathbb{Z}$, namely $\theta_\ell = \int_0^1 e^{-2i\ell\pi x} f(x) dx$. The model (1.1) can then be rewritten as

$$\begin{aligned} c_{m,\ell} &:= \int_0^1 e^{-2i\ell\pi x} dY_m(x) = \theta_\ell e^{-i2\pi\ell\tau_m} + \epsilon_m z_{\ell,m} \\ &= \theta_\ell \gamma_\ell + \xi_{\ell,m} + \epsilon_m z_{\ell,m}, \end{aligned} \quad (1.5)$$

with $\xi_{\ell,m} = \theta_\ell e^{-i2\pi\ell\tau_m} - \theta_\ell \gamma_\ell$, and where $z_{\ell,m}$ are iid $N_{\mathbb{C}}(0, 1)$ variables, i.e. complex Gaussian variables with zero mean and such that $\mathbb{E}|z_{\ell,n}|^2 = 1$.

Thus, we can compute the sample mean $\tilde{c}_\ell$ of the ℓ^{th} Fourier coefficient over the n curves as

$$\tilde{c}_\ell = \frac{1}{n} \sum_{m=1}^n c_{\ell,m} = \theta_\ell \tilde{\gamma}_\ell + \epsilon \eta_\ell = \theta_\ell \gamma_\ell + \xi_\ell + \epsilon \eta_\ell, \quad (1.6)$$

with $\tilde{\gamma}_\ell = \frac{1}{n} \sum_{m=1}^n e^{-i2\pi\ell\tau_m}$, $\xi_\ell = \frac{1}{n} \sum_{m=1}^n \xi_{\ell,m}$, $\epsilon^2 = \frac{1}{n} \sum_{m=1}^n \epsilon_m^2$, and where the η_ℓ 's are iid complex Gaussian variables with zero mean and such that $\mathbb{E}|\eta_\ell|^2 = \frac{1}{n}$. The average Fourier coefficients $\tilde{c}_\ell$ in equation (1.6) can thus be viewed as a set of observations which is very close to a sequence space formulation of a statistical inverse problem as described e.g by [6]. As in model (1.4) the additive error term ξ_ℓ is asymptotically Gaussian, however its variance is $\frac{1}{n}|\theta_\ell|^2(1-|\gamma_\ell|^2)$ which is obviously unknown as it depends on f , and thus it has to be estimated.

If we assume that the density g of the random shifts is known, one can perform a deconvolution step by taking

$$\hat{\theta}_\ell = \frac{\tilde{c}_\ell}{\gamma_\ell} = \theta_\ell \frac{\tilde{\gamma}_\ell}{\gamma_\ell} + \epsilon \frac{\eta_\ell}{\gamma_\ell}. \quad (1.7)$$

to estimate the Fourier coefficients of f since, for large n , $\frac{\tilde{\gamma}_\ell}{\gamma_\ell}$ is close to 1 by the strong law of large numbers.

Based on the $\hat{\theta}_\ell$'s, two types of estimators are studied. The simplest one uses spectral cut-off with a cutting frequency depending on the smoothness assumptions on f , and is thus non-adaptive. The second estimator is based on wavelet thresholding and is shown to be adaptive using the procedure developed in [17]. Note that all the theoretical results are presented for the case where the coefficients γ_ℓ are known. Such a framework is commonly used in nonparametric regression and inverse problems to obtain consistency results and to study asymptotic rates of convergence, where it is generally supposed that the law of the additive error is Gaussian with zero mean and *known* variance ϵ^2 , see e.g [17] [27], [6]. In model (1.1), the random shifts may be viewed as a second source of noise and for the theoretical analysis of this problem the law of this other random noise is also supposed to be known. However, for some special classes of densities g , it is possible to derive data-based estimator $\hat{\gamma}_\ell$ of the γ_ℓ 's, see Section 5.

1.4 Previous work in mean pattern estimation

The problem of estimating the common shape of a set of curves that differ only by a time transformation is usually referred to as the curve registration problem in statistics, and it has received a lot of attention over the last two decades, see e.g [10], [11], [2], [30], [34], [21]. However, in these papers, an asymptotic study as the number of curves n grows to infinity is not considered.

In the simplest case of shifted curves, various approaches have been developed. Self-modelling regression methods proposed by [18] are semiparametric models where each observed curve is a parametric transformation of a common regression function, and estimation of the shape function in such models is studied in [18] with asymptotic in the number of curves. Based on a model with a fixed number n of curves, semiparametric estimation of deformation parameters and nonparametric estimation of the shape function is proposed in [22] and [33]. A generalization of this approach for the estimation of scaling, rotation and translation parameters for two-dimensional images is proposed in [4]. Estimation of a common shape for randomly shifted curves and asymptotic in n is also considered in [31]. There is also a huge literature in image analysis on mean pattern estimation, and some papers have recently addressed the problem of estimating the common shape of a set of similar images with asymptotic in the number of images, see e.g. [1], [23], [3] and references therein.

However, in all the above cited papers rates of convergence and optimality of the proposed estimators are generally not studied, and adaptive estimation of the common shape function in such models has not been considered yet.

1.5 Organization of the paper

In Section 2, we consider a linear but non-adaptive estimator based on spectral cut-off. In Section 3, a nonlinear and adaptive estimator based on wavelet thresholding is studied, and upper bound for the minimax risk are studied over Besov balls. In Section 4, we derive lower bounds for the minimax risk. In Section 5, it is explained how one can estimate the eigenvalues γ_ℓ for some specific class of densities g . Finally, in Section 6, some numerical examples are proposed to illustrate the performances of our approach and to compare them with another algorithm proposed in the literature. All proofs are deferred to a technical Appendix at the end of the paper.

2 Linear estimation of the common shape and upper bounds for the risk for Sobolev balls

2.1 Risk decomposition

For $\ell \in \mathbb{Z}$, a linear estimator of the θ_ℓ 's is given by $\hat{\theta}_\ell^\lambda = \lambda_\ell \frac{\tilde{c}_\ell}{\gamma_\ell}$, where $\lambda = (\lambda_\ell)_{\ell \in \mathbb{Z}}$ is a sequence of nonrandom weights called a filter. An estimator $\hat{f}_{n,\lambda}$ of f is then obtained via the inverse Fourier transform $\hat{f}_{n,\lambda}(x) = \sum_{\ell \in \mathbb{Z}} \hat{\theta}_\ell^\lambda e^{-i2\pi\ell x}$, and thanks to the Parseval's relation, the risk of this estimator is given by $\mathcal{R}(\hat{f}_{n,\lambda}, f) = \mathbb{E} \sum_{\ell \in \mathbb{Z}} |\hat{\theta}_\ell - \theta_\ell|^2$. The problem is then to choose the sequence $(\lambda_\ell)_{\ell \in \mathbb{Z}}$ in an optimal way. The following proposition gives the bias-variance decomposition of $\mathcal{R}(\hat{f}_{n,\lambda}, f)$.

Proposition 2.1 *For any given nonrandom filter λ , the risk of the estimator $\hat{f}_{n,\lambda}$ can be decomposed as*

$$\mathcal{R}(\hat{f}_{n,\lambda}, f) = \underbrace{\sum_{\ell \in \mathbb{Z}} (\lambda_\ell - 1)^2 |\theta_\ell|^2}_{\text{Bias}} + \underbrace{\frac{1}{n} \sum_{\ell \in \mathbb{Z}} \lambda_\ell^2 \left[|\theta_\ell|^2 \left(\frac{1}{|\gamma_\ell|^2} - 1 \right) + \frac{\epsilon^2}{|\gamma_\ell|^2} \right]}_{\text{Variance}}. \quad (2.1)$$

Note that the decomposition (2.1) does not correspond exactly to the classical bias-variance decomposition for linear inverse problems. Indeed, the variance term in (2.1) differs from the classical expression of the variance for linear estimator in statistical inverse problems which would be in our notations $\epsilon^2 \sum_{\ell \in \mathbb{Z}} \frac{\lambda_\ell^2}{|\gamma_\ell|^2}$. Hence, contrary to classical inverse problems, the variance term of the risk depends also on the Fourier coefficients θ_ℓ of the unknown function f to recover.

2.2 Linear estimation

Let us introduce the following smoothness class of functions which can be identified with a periodic Sobolev ball

$$H_s(A) = \left\{ f \in L^2([0, 1]) ; \sum_{\ell \in \mathbb{Z}} (1 + |\ell|^{2s}) |\theta_\ell|^2 \leq A \right\}$$

for some constant A and some smoothness parameter $s > 0$, where $\theta_\ell = \int_0^1 e^{-2i\ell\pi x} f(x) dx$. Now consider a linear estimator obtained by spectral cut-off, i.e. for a projection filter of the form $\lambda_\ell^M = \mathbb{1}_{|\ell| \leq M}$ for some integer M . For an appropriate choice of M , the following proposition gives the asymptotic behavior of the risk $\mathcal{R}(\hat{f}_{n, \lambda^M}, f)$.

Proposition 2.2 *Assume that f belongs to $H_s(A)$ for some real $s > 1/2$ and $A > 0$, and that g satisfies (1.1) i.e. polynomial decay of the γ_ℓ 's. Then, if $M = M_n$ is chosen such that $M_n \sim n^{\frac{1}{2s+2\nu+1}}$, then there exists a constant C not depending on n such that as $n \rightarrow +\infty$*

$$\sup_{f \in H_s(A)} \mathcal{R}(\hat{f}_{n, \lambda^M}, f) \leq C n^{-\frac{2s}{2s+2\nu+1}}.$$

The above choice for M_n depends on the smoothness s of the function f which is generally unknown in practice and such a spectral cut-off estimator is thus called non-adaptive. Moreover, the result is only suited for smooth functions since Sobolev balls $H_s(A)$ for $s > 1/2$ are not suited to model shape functions f which may have singularities such as points of discontinuity.

3 Nonlinear estimation with Meyer wavelets and upper bounds for the risk for Besov balls

The advantages of wavelet methods is their ability in estimating spatially inhomogeneous functions, and in recovering local features such as peaks or discontinuities. They can be used to estimate functions in Besov spaces with optimal rates of convergence, and have therefore received special attention in the literature over the last two decades, see e.g [9]. Wavelets have been successfully used for various inverse problems [8], and for the specific case of deconvolution a special class of band-limited wavelets introduced by [26] have recently received special attention in nonparametric regression, see [17] and [27].

3.1 Wavelet decomposition and the periodized Meyer wavelet basis

This wavelet basis is derived through the periodization of the Meyer wavelet basis of $L^2(\mathbb{R})$. It is constructed from a scaling function ϕ^* with Fourier transform

$$\tilde{\phi}(\omega) = \int_{\mathbb{R}} \phi^*(x) e^{-i\omega x} dx = \begin{cases} \frac{\tilde{h}(\omega/2)}{\sqrt{2}} & \text{if } |\omega| \leq 4\pi/3, \\ 0 & \text{if } |\omega| > 4\pi/3, \end{cases}$$

where $\tilde{h} : \mathbb{C} \rightarrow \mathbb{R}$ is a smooth function (see [24], [17] for further details). In our simulations, we use for $\tilde{h}$ a polynomial function of degree 3 to define the so-called Meyer window. Hence Meyer wavelets are band-limited functions which makes them very useful for deconvolution problems. Indeed, let (ϕ^*, ψ^*) be the Meyer scaling and wavelet function respectively. Scaling and wavelet function at scale $j \geq 0$ are defined by

$$\phi_{j,k}^*(x) = 2^{j/2} \phi^*(2^j x - k) \text{ and } \psi_{j,k}^*(x) = 2^{j/2} \psi^*(2^j x - k), \quad k = 0, \dots, 2^j - 1.$$

As in [17] and [27], one can then define the periodized Meyer wavelet basis of $L^2([0, 1])$ by periodizing the functions (ϕ^*, ψ^*) i.e. for $k = 0, \dots, 2^j - 1$

$$\phi_{j,k}(x) = 2^{j/2} \sum_{i \in \mathbb{Z}} \phi^*(2^j(x+i) - k) \text{ and } \psi_{j,k}(x) = 2^{j/2} \sum_{i \in \mathbb{Z}} \psi^*(2^j(x+i) - k).$$

For any function f of $L^2([0, 1])$, its wavelet decomposition can be written as:

$$f = \sum_{k=0}^{2^{j_0}-1} c_{j_0,k} \phi_{j_0,k} + \sum_{j=j_0}^{+\infty} \sum_{k=0}^{2^j-1} \beta_{j,k} \psi_{j,k},$$

where $c_{j_0,k} = \int_0^1 f(x) \phi_{j_0,k}(x) dx$, $\beta_{j,k} = \int_0^1 f(x) \psi_{j,k}(x) dx$ and $j_0 \geq 0$ denotes the usual coarse level of resolution. Moreover, the squared norm of f is given by

$$\|f\|^2 = \sum_{k=0}^{2^{j_0}-1} c_{j_0,k}^2 + \sum_{j=j_0}^{+\infty} \sum_{k=0}^{2^j-1} \beta_{j,k}^2.$$

It is well known that Besov spaces can be characterized in terms of wavelet coefficients (see e.g [17]). Let $s > 0$ denote the usual smoothness parameter, then for the Meyer wavelet basis and for a Besov ball $B_{p,q}^s(A)$ of radius $A > 0$ with $1 \leq p, q \leq \infty$, one has that $B_{p,q}^s(A) = \left\{ f \in L^2([0, 1]) : \left(\sum_{k=0}^{2^{j_0}-1} |c_{j_0,k}|^p \right)^{\frac{1}{p}} + \left(\sum_{j=j_0}^{+\infty} 2^{j(s+1/2-1/p)q} \left(\sum_{k=0}^{2^j-1} |\beta_{j,k}|^p \right)^{\frac{q}{p}} \right)^{\frac{1}{q}} \leq A \right\}$ with the respective above sums replaced by maximum if $p = \infty$ or $q = \infty$.

Meyer wavelets can be used to efficiently compute the coefficients $c_{j,k}$ and $\beta_{j,k}$ by using the Fourier transform. Indeed, thanks to the Plancherel's identity, one obtains that

$$\beta_{j,k} = \sum_{\ell \in \Omega_j} \psi_{\ell}^{j,k} \theta_{\ell}, \quad (3.1)$$

where $\psi_{\ell}^{j,k} = \int_0^1 \psi_{j,k}(x) e^{-i2\pi \ell x} dx$ denote the Fourier coefficients of $\psi_{j,k}$ and $\Omega_j = \{\ell \in \mathbb{Z}; \psi_{\ell}^{j,k} \neq 0\}$. As Meyer wavelets $\psi_{j,k}$ are band-limited Ω_j is a finite subset set of $[-2^{j+2}c_0, -2^j c_0] \cup [2^j c_0, 2^{j+2}c_0]$ with $c_0 = 2\pi/3$ (see [17]), and fast algorithms for computing the above sum have been proposed by [19] and [29]. The coefficients $c_{j_0,k}$ can be computed analogously with ϕ instead of ψ and $\Omega_{j_0} = \{\ell \in \mathbb{Z}; \phi_{\ell}^{j_0,k} \neq 0\}$ instead of Ω_j .

Hence, the noisy Fourier coefficients $\hat{\theta}_{\ell}$ given by (1.7) can be used to quickly compute the following empirical wavelet coefficients of f as

$$\hat{\beta}_{j,k} = \sum_{\ell \in \Omega_j} \psi_{\ell}^{j,k} \hat{\theta}_{\ell} \text{ and } \hat{c}_{j_0,k} = \sum_{\ell \in \Omega_{j_0}} \phi_{\ell}^{j_0,k} \hat{\theta}_{\ell}. \quad (3.2)$$

3.2 Nonlinear estimation via hard-thresholding

It is well known that adaptivity can be obtained by using nonlinear estimators based on appropriate thresholding of the estimated wavelet coefficients (see e.g [9]). A non-linear estimator by hard-thresholding is defined by

$$\hat{f}_n^h = \sum_{k=0}^{2^{j_0}-1} \hat{c}_{j_0,k} \phi_{j_0,k} + \sum_{j=j_0}^{j_1} \sum_{k=0}^{2^j-1} \hat{\beta}_{j,k} \mathbb{1}_{\{|\hat{\beta}_{j,k}| \geq \lambda_{j,k}\}} \psi_{j,k} \quad (3.3)$$

where the $\lambda_{j,k}$'s are appropriate thresholds (positive numbers), and j_1 is the finest resolution level used for the estimation. As shown by [17], for periodic deconvolution the choice for j_1 and the thresholds $\lambda_{j,k}$ typically depends on the degree ν of ill-posedness of the problem. More

precisely, Theorem 1 in [17] asserts that upper bounds for the minimax risk can be obtained if there exists two constant C_1, C_2 such that for all $f \in B_{p,q}^s(A)$ (with appropriate assumptions on s, p, q, ν) the following conditions are satisfied

$$2^{j_1} = \mathcal{O}\left(\frac{n}{\log(n)}\right)^{\frac{1}{2\nu+1}}, \quad (3.4)$$

$$\mathbb{E}|\hat{\beta}_{j,k} - \beta_{j,k}|^4 \leq C_1 \left(2^{2j\nu} \frac{\log(n)}{n}\right)^2, \quad (3.5)$$

$$\mathbb{P}\left(|\hat{\beta}_{j,k} - \beta_{j,k}| \geq \lambda_j\right) \leq C_2 \left(\frac{\log(n)}{n}\right)^2, \quad (3.6)$$

for all $0 \leq k \leq 2^j - 1$ and $j_0 \leq j \leq j_1$, and where λ_j is an appropriate threshold that satisfies

$$\lambda_j \leq C 2^{j\nu} \sqrt{\frac{2\log(n)}{n}}, \quad (3.7)$$

where C is a sufficiently large constant not depending on n, j, k and f .

To control moments of $\hat{\beta}_{j,k}$, one needs the following assumption on the decay of the density $g(x)$ as $|x| \rightarrow +\infty$

Assumption 3.1 *There exists a constant $C > 0$ and a real $\alpha > 1$ such that the density g satisfies $g(x) \leq \frac{C}{1+|x|^\alpha}$ for all $x \in \mathbb{R}$.*

Note that Assumption 3.1 is not a very restrictive condition as g is supposed to be an integrable function on $\mathbb{R}$. This can also be viewed as a sufficient condition to ensure the existence of the density $G(x)$ introduced in (1.3).

Proposition 3.1 *Let $1 \leq p \leq \infty$, $1 \leq q \leq \infty$, $s - 1/p + 1/2 > 0$ and $A > 0$. Assume that g satisfies Assumptions 1.1 and 3.1. Then, there exist positive constants C_3 and C_4 such that for any $j \geq j_0 \geq 0$, $0 \leq k \leq 2^j - 1$ and all $f \in B_{p,q}^s(A)$, $\mathbb{E}|\hat{c}_{j_0,k} - c_{j_0,k}|^2 \leq C_3 \frac{2^{2j_0\nu}}{n}$, $\mathbb{E}|\hat{\beta}_{j,k} - \beta_{j,k}|^2 \leq C_3 \frac{2^{2j\nu}}{n}$, and $\mathbb{E}|\hat{\beta}_{j,k} - \beta_{j,k}|^4 \leq C_4 \left(\frac{2^{2j\nu}}{n^2} + \frac{2^{j(4\nu+1)}}{n^3}\right)$.*

Proposition 3.1 shows that the variance of the empirical wavelet coefficients is proportional to $\frac{2^{2j\nu}}{n}$ which comes from the amplification of the noise by the inversion of the convolution operator. Moreover, it also shows that if $2^{j_1} = \mathcal{O}\left(\frac{n}{\log(n)}\right)^{\frac{1}{2\nu+1}}$, then condition (3.5) is satisfied for all $j_0 \leq j \leq j_1$.

Generally the choice of the threshold $\lambda_{j,k}$ is done by controlling the probability of deviation of the empirical wavelet coefficients $\hat{\beta}_{j,k}$ from the true wavelet coefficient $\beta_{j,k}$, which is given by the following proposition:

Proposition 3.2 *Let $f \in L^2([0, 1])$, $n \geq 1$ and $j \geq 0$. Suppose that g satisfies Assumption 3.1. For $0 \leq k \leq 2^j - 1$ and $\theta_\ell = \int_0^1 f(x) e^{-i2\pi\ell x} dx$, define*

$$\sigma_j^2 = 2^{-j} \epsilon^2 \sum_{\ell \in \Omega_j} |\gamma_\ell|^{-2}, V_j^2 = \|g\|_\infty^2 2^{-j} \sum_{\ell \in \Omega_j} \frac{|\theta_\ell|^2}{|\gamma_\ell|^2} \text{ and } \delta_j = 2^{-j/2} \sum_{\ell \in \Omega_j} \frac{|\theta_\ell|}{|\gamma_\ell|}.$$

with $\|g\|_\infty = \sup_{x \in \mathbb{R}} \{g(x)\}$. Let $t > 0$, then,

$$\mathbb{P}\left(|\hat{\beta}_{j,k} - \beta_{j,k}| \geq 2 \max\left(\sigma_j \sqrt{\frac{2t}{n}}, \sqrt{\frac{2V_j^2 t}{n}} + \delta_j \frac{t}{3n}\right)\right) \leq 2 \exp(-t).$$

Proposition 3.2 suggests to take level-dependent thresholds of the form

$$\lambda_{j,k}^* = \lambda_j^* = 2 \max \left(\sigma_j \sqrt{\frac{2\eta \log(n)}{n}}, \sqrt{\frac{2\eta V_j^2 \log(n)}{n}} + \delta_j \frac{\eta \log(n)}{3n} \right) \quad (3.8)$$

where $\eta > 0$ is constant whose choice has to be discussed. If $\eta \geq 2$, then Proposition 3.2 implies that $\mathbb{P}(|\hat{\beta}_{j,k} - \beta_{j,k}| \geq \lambda_j^*) \leq 2n^{-2} \leq 2 \left(\frac{\log(n)}{n} \right)^2$, and thus the threshold λ_j^* satisfies condition (3.6). Moreover, Lemma A.2 (see the Appendix) states that the Fourier coefficients θ_ℓ are uniformly bounded for all $f \in B_{p,q}^s(A)$ (provided $s - 1/p + 1/2 > 0$). Hence, since Ω_j is a finite subset set of $[-2^{j+2}c_0, -2^j c_0] \cup [2^j c_0, 2^{j+2}c_0]$, one can easily check that there exists a constant C such that under Assumption 1.1

$$\lambda_j^* \leq C 2^{j\nu} \sqrt{\frac{2 \log(n)}{n}}, \quad (3.9)$$

for all $f \in B_{p,q}^s(A)$. Hence, the threshold λ_j^* satisfies also condition (3.7).

The first term in the maximum (3.8) is the classical universal threshold with heteroscedastic variance σ_j^2 which corresponds to an upper bound of the variance of the Gaussian term $\epsilon \sum_{\ell \in \Omega_j} \frac{\eta_\ell}{\gamma_\ell}$ in the expression of $\hat{\beta}_{j,k}$. However, the second term in the maximum (3.8) depends on the modulus of the unknown Fourier coefficients θ_ℓ , and thus the thresholds λ_j^* cannot be used in practice. As already explained in the introduction, this comes from the fact that the variance of the error term ξ_ℓ in model (1.6) has to be estimated.

First, remark that if f is such that

$$|\theta_\ell|^2 \max(\|g\|_\infty, 1) \leq \epsilon^2 \text{ for all } \ell \in \Omega_j \text{ and } j \geq j_0, \quad (3.10)$$

then the threshold in (3.8) simplifies to

$$\lambda_{j,k}^* = \lambda_j^* = 2 \left(\sigma_j \sqrt{\frac{2\eta \log(n)}{n}} + 2^{-j/2} \sum_{\ell \in \Omega_j} |\gamma_\ell|^{-1} \frac{\eta \log(n)}{3n} \right) \quad (3.11)$$

since under condition (3.10) $V_j^2 \leq \sigma_j^2$. Hence, for n sufficiently large $\lambda_j^* \approx 2\sigma_j \sqrt{\frac{2\eta \log(n)}{n}}$, and thus one retrieves the classical form of a level dependent threshold for wavelet deconvolution in the white noise model as in [17].

Obviously, an assumption such as (3.10) would not hold for all f in some arbitrary Besov ball $f \in B_{p,q}^s(A)$, and one must find a data-based upper bound for $|\theta_\ell|^2$. To do so, one can remark that an unbiased estimator of $|\theta_\ell|^2$ is given by

$$|\hat{\theta}_\ell|^2 = \frac{1}{n} \sum_{m=1}^n |c_{m,\ell}|^2 - \epsilon^2, \quad (3.12)$$

where $c_{m,\ell} = \theta_\ell e^{-i2\pi\ell\tau_m} + \epsilon z_{\ell,m}$, see equation (1.5). This gives a very accurate estimation of $|\theta_\ell|$ in the sense of the following lemma:

Lemma 3.1 *Let $f \in L^2([0,1])$, $n \geq 1$. Then, for any $j \geq 0$ and all $\ell \in \Omega_j$*

$$\mathbb{P} \left(\sqrt{|\hat{\theta}_\ell|^2 + \epsilon^2} - \epsilon \sqrt{\frac{2t}{n}} - \epsilon \leq |\theta_\ell| \leq \sqrt{|\hat{\theta}_\ell|^2 + \epsilon^2} + \epsilon \sqrt{\frac{2t}{n}} \right) \geq 1 - 2 \exp(-t),$$

for any $t > 0$.

Based on Lemma 3.1, we define the following random thresholds λ_j

$$\lambda_{j,k} = \lambda_j = 2 \max \left(\sigma_j \sqrt{\frac{2\eta \log(n)}{n}}, \sqrt{\frac{2\hat{V}_j^2 \eta \log(n)}{n}} + \hat{\delta}_j \frac{\eta \log(n)}{3n} \right) \quad (3.13)$$

with $\eta \geq 2$, $\hat{V}_j^2 = \|g\|_\infty^2 2^{-j} \sum_{\ell \in \Omega_j} \frac{|\tilde{\theta}_\ell|^2}{|\gamma_\ell|^2}$ and $\hat{\delta}_j = 2^{-j/2} \sum_{\ell \in \Omega_j} \frac{|\tilde{\theta}_\ell|}{|\gamma_\ell|}$, where

$$|\tilde{\theta}_\ell| = \sqrt{|\hat{\theta}_\ell|^2 + \epsilon^2} + \epsilon \sqrt{\frac{2 \log(n^2 2^j)}{n}}.$$

The quantity $|\tilde{\theta}_\ell|$ is a data-based upper bound for $|\theta_\ell|$ that is plugged into the definition of the ideal threshold λ_j^* to obtain the data-driven thresholds λ_j defined by (3.13). Note that such thresholds are not difficult to calculate in practice, and more details on their computation are given in Section 6 on numerical experiments. Then, the following proposition holds:

Proposition 3.3 *Let $f \in L^2([0, 1])$ and $n \geq 1$. Then, there exists a constant C not depending on f and n , such that for all $j \geq 0$ and $0 \leq k \leq 2^j - 1$*

$$\mathbb{P} \left(|\hat{\beta}_{j,k} - \beta_{j,k}| \geq \lambda_j \right) \leq C n^{-2}.$$

Combining the above arguments, we finally arrive at the following theorem which gives an upper bound for the minimax risk over a large class of Besov balls.

Theorem 3.1 *Assume that g satisfies Assumptions 1.1 and 3.1. Let j_1 and j_0 be the largest integers such that $2^{j_1} \leq \left(\frac{n}{\log(n)} \right)^{\frac{1}{2\nu+1}}$ and $2^{j_0} \leq \log(n)$. Let $\hat{f}_n^h$ be the non-linear estimator obtained by hard-thresholding with the above choice for j_1 and j_0 , and using the thresholds λ_j defined by equation (3.13). Let $1 \leq p \leq \infty$, $1 \leq q \leq \infty$ and $A > 0$. Let $p' = \min(2, p)$, $s' = s + 1/2 - 1/p$, and assume that $s \geq 1/p'$.*

If $s \geq (2\nu + 1)(1/p - 1/2)$, then

$$\sup_{f \in B_{p,q}^s(A)} \|\hat{f}_n^h - f\|^2 = \mathcal{O} \left(n^{-\frac{2s}{2s+2\nu+1}} (\log n)^\beta \right) \text{ with } \beta = \frac{2s}{2s+2\nu+1}.$$

If $s < (2\nu + 1)(1/p - 1/2)$, then

$$\sup_{f \in B_{p,q}^s(A)} \|\hat{f}_n^h - f\|^2 = \mathcal{O} \left(\left(\frac{n}{\log(n)} \right)^{-\frac{2s'}{2s'+2\nu}} \right).$$

In standard periodic deconvolution in the white noise model (see e.g. [17]), there exists two different upper bounds for the minimax rate which are usually referred to as the dense case ($s \geq (2\nu + 1)(1/p - 1/2)$) when the hardest functions to estimate are spread uniformly over $[0, 1]$, and the sparse case ($s < (2\nu + 1)(1/p - 1/2)$) when the worst functions to estimate have only one non-vanishing wavelet coefficient. Theorem 3.1 shows that a similar phenomenon holds for the model (1.1), and to the best of our knowledge, this is a new result.

In the following section, the rate $n^{-\frac{2s}{2s+2\nu+1}}$ is shown to be, in the dense case, a lower bound for the asymptotic decay of the minimax risk $\mathcal{R}_n(B_{p,q}^s(A))$. Hence, when the the hardest functions to estimate are spread uniformly over $[0, 1]$, the estimator $\hat{f}_n^h$ is near-optimal up to a logarithmic term. This phenomena is well known in nonparametric regression with wavelets, see e.g [9], [27], and this extra logarithmic factor is usually referred to as the price for adaptivity. Here, adaptivity must be understood in the sense that the proposed threshold and the choice of the finest resolution level j_1 does not depend on the smoothness parameter s . Recall that the space

$B_{p,q}^s(A)$) with $1 \leq p < 2$ contains piecewise smooth functions with local irregularities such as peaks or discontinuities, while the space $B_{2,2}^s(A)$ is a Sobolev ball if s is not an integer. Hence, contrary to the linear estimator proposed in Section 2, the above described non-linear estimator is suitable for the estimation of irregular functions, and is adaptive with respect to the unknown smoothness parameter s .

4 Minimax lower bound

The following theorem gives an asymptotic lower bound on the minimax risk $\mathcal{R}_n(B_{p,q}^s(A))$ for a large class of Besov balls.

Theorem 4.1 *Let $1 \leq p \leq \infty$, $1 \leq q \leq \infty$ and $A > 0$. Suppose that g satisfies Assumption 1.1. Let $p' = \min(2, p)$. Assume that $s \geq 1/p'$ and $\nu > 1/2$.*

If $s \geq (2\nu + 1)(1/p - 1/2)$ and $s > 2\nu + 1$ (dense case), there exists a constant M_1 depending only on A, s, p, q such that

$$\mathcal{R}_n(B_{p,q}^s(A)) \geq M_1 n^{-\frac{2s}{2s+2\nu+1}} \text{ as } n \rightarrow +\infty$$

In the dense case, the hardest functions to estimate are spread uniformly over the interval $[0, 1]$, and the proof is based on an adaptation of Assouad's cube technique (see e.g Lemma 10.2 in [14]) to the specific setting of model (1.1). Lower bounds for minimax risk are classically derived by controlling the probability for the likelihood ratio (in the statistical model of interest) of being strictly greater than some constant uniformly over an appropriate set of test functions. To derive Theorem 4.1, we show that one needs to control the expectation over the random shifts of the likelihood ratio associated to model (1.1), and not only the likelihood ratio itself. Hence, the proof of Theorem 4.1 is not a direct and straightforward adaptation of Assouad's cube technique or Lemma 10.1 in [14] as used classically in a standard white noise model to derive minimax risk in nonparametric deconvolution in the dense case. For more details, we refer to the proof of Theorem 4.1 in the Appendix.

Deriving minimax risk in the dense case for the model (1.1) is rather difficult and the proof is quite long and technical. In the sparse case, finding lower bounds for the minimax rate is also a difficult task. We believe that this could be done by adapting to model (1.1) a result by [20] which yields a lower bound for a specific problem of distinguishing between a finite number of hypotheses (see Lemma 10.1 in [14]). However, this is far beyond the scope of this paper and we leave this problem open for future work.

5 Estimation of the eigenvalues γ_ℓ

Define the following specific class of densities

$$\mathcal{F}_+ = \left\{ g : \mathbb{R} \rightarrow \mathbb{R}^+, \int_{\mathbb{R}} g(x) dx = 1, \text{ with } \gamma_\ell = \int_{\mathbb{R}} e^{-i2\pi\ell x} g(x) dx = \overline{\gamma_\ell} \text{ and } \gamma_\ell > 0 \text{ for all } \ell \in \mathbb{Z} \right\}.$$

Examples of densities belonging to $\mathcal{F}_+$ include the Gaussian or Laplace distribution with zero mean.

Next we give a series of arguments to explain how one can estimate the γ_ℓ 's if $g \in \mathcal{F}_+$. First recall that the quantity $\frac{1}{n} \sum_{m=1}^n |c_{m,\ell}|^2 - \frac{1}{n} \sum_{m=1}^n \epsilon_m^2$ is an unbiased estimator of $|\theta_\ell|^2$. Similarly, one can remark that $|\tilde{c}_\ell|^2$ is an unbiased estimator of $|\gamma_\ell|^2 |\theta_\ell|^2$, where by definition $\tilde{c}_\ell = \frac{1}{n} \sum_{m=1}^n c_{m,\ell}$. Therefore, this suggests that $|\gamma_\ell|^2$ can be estimated by

$$\delta_\ell = \frac{|\tilde{c}_\ell|^2}{\frac{1}{n} \sum_{m=1}^n |c_{m,\ell}|^2 - \frac{1}{n} \sum_{m=1}^n \epsilon_m^2},$$

and if one assumes that $g \in \mathcal{F}_+$ then an estimator for γ_ℓ is given by $\hat{\gamma}_\ell = \sqrt{\delta_\ell}$. In such a case, one has immediately the following result by applying the strong law of large numbers:

Lemma 5.1 *Assume that $g \in \mathcal{F}_+$ and that $\theta_\ell \neq 0$ for all $\ell \in \mathbb{Z}$. Moreover suppose that ϵ_m^2 is known for all $m = 1, \dots, n$. Then, as $n \rightarrow +\infty$ $\hat{\gamma}_\ell \rightarrow \gamma_\ell$ almost surely.*

The estimated value $\hat{\gamma}_\ell$ can then be plugged into the definition of the wavelet estimator and the thresholds given in Section 3.

6 Numerical experiments

We compare our approach with the Procrustean mean which is a standard algorithm commonly used to extract a mean pattern. The Procrustean mean is based on an alternative scheme between estimation of the shifts and averaging of back-transformed curves given estimated values of the shifts parameters, see e.g [34], [18]. To be more precise it consists of an initialization step $\hat{f}_0 = \frac{1}{n} \sum_{m=1}^n Y_m$ which is the simple average of the observed curves that is taken as a first reference mean pattern. Then, at iteration $1 \leq i \leq i_{\max}$, it computes for all $1 \leq m \leq n$ an estimation $\hat{\tau}_{m,i}$ of the m -th shift as $\hat{\tau}_{m,i} = \arg \min_{\tau \in \mathbb{R}} \|Y_m(\cdot + \tau) - \hat{f}_{i-1}\|^2$ and then takes $\hat{f}_i(x) = \frac{1}{n} \sum_{m=1}^n Y_m(x + \hat{\tau}_{m,i})$ as a new reference mean pattern. This is repeated until the estimated reference curve does not change, and usually the algorithm converges in a few steps (we took $i_{\max} = 3$). In all simulations, we used the wavelet toolbox Wavelab [5] and the WaveD algorithm developed by [29] for fast deconvolution with Meyer wavelets.

6.1 Estimation when the γ_ℓ 's are unknown

For the mean pattern f to recover, we consider the four tests functions shown in Figures 1a-4a. Then, we simulate $n = 200$ randomly shifted curves with shifts following a Laplace distribution $g(x) = \frac{1}{\sqrt{2}\sigma} \exp\left(-\sqrt{2}\frac{|x|}{\sigma}\right)$ with $\sigma = 0.1$. Gaussian noise with a moderate variance (different to that used in the Laplace distribution) is then added to each curve. A subsample of 10 curves is shown in Figures 1b- 4b for each test function, and the average of the observed curves, referred to as the direct mean in what follows, is displayed in Figures 1c- 4c. Note this gives a poor estimation of the mean pattern.

The Fourier coefficients of the density g are given by $\gamma_\ell = \frac{1}{1+2\sigma^2\pi^2\ell^2}$ which corresponds to a degree of ill-posedness $\nu = 2$. Hence, this density belongs to the class $\mathcal{F}_+$ defined by (5.1), and thus an estimate $\hat{\gamma}_\ell$ of γ_ℓ can be performed as explained in Section 5. After deconvolution of the direct mean, Theorem 3.1 suggests to take a threshold of the form $\lambda_j = 2 \max \left(\sigma_j \sqrt{\frac{2\eta \log(n)}{n}}, \sqrt{\frac{2\tilde{V}_j^2 \eta \log(n)}{n}} + \hat{\delta}_j \frac{\eta \log(n)}{3n} \right)$. In our simulations we have found that choosing η between 1 and 2 gives quite satisfactory results. However, some quantities in the definition of λ_j have to be estimated. The following numerical experiments are thus given for the threshold

$$\hat{\lambda}_j = 2 \max \left(\hat{\sigma}_j \sqrt{\frac{2 \log(n)}{n}}, \sqrt{\frac{2\tilde{V}_j^2 \log(n)}{n}} + \tilde{\delta}_j \frac{\log(n)}{3n} \right)$$

with

$$\tilde{V}_j^2 = \|g\|_\infty 2^{-j} \sum_{\ell \in \Omega_j} \frac{|\tilde{\theta}_\ell|^2}{|\hat{\gamma}_\ell|^2} \text{ and } \tilde{\delta}_j = 2^{-j/2} \sum_{\ell \in \Omega_j} \frac{|\tilde{\theta}_\ell|}{|\hat{\gamma}_\ell|},$$

where $\hat{\sigma}_j = 2^{-j} \hat{\epsilon}^2 \sum_{\ell \in \Omega_j} |\hat{\gamma}_\ell|^{-2}$ with $\hat{\epsilon}^2 = \frac{1}{n} \sum_{m=1}^n \epsilon_m^2$, and where the variance ϵ_m^2 of the noise for the m -th curve is easily estimated using the wavelet coefficients at the finest resolution level. Note that this threshold is quite simple to compute using the Fast Fourier Transform to calculate the $|\tilde{\theta}_\ell|$'s, and the fact that the set of frequencies Ω_j can be easily obtained using WaveLab.

Then, we took $j_0 = 3 \approx \log_2(\log(n))$, but the choice $j_1 \approx \frac{1}{2\nu+1} \log_2(\frac{n}{\log(n)})$ is obviously too small. So in our simulations, j_1 is chosen to be the maximum resolution level allowed by the discretization i.e. $j_1 = \log_2(N) - 1 = 7$. The modulus of the empirical wavelet coefficients together with the value of the threshold $\hat{\lambda}_j$ are shown in Figures 1d -4d for each test function, and the resulting estimators are displayed in Figures 1e -4e. The Procrustean mean is displayed in Figures 1f -4f, and one can see that both methods give similar and quite satisfactory results. In particular, it should be noted that these results are obtained in the case of an unknown density g which confirms the quality of the estimation procedure proposed in Section 5 for the γ_ℓ 's. For reasons of space a detailed simulation study is not given, but it has been found that the good performances of the wavelet-based estimator remain consistent across other standard test signals.




Figure 1: Wave function. (a) Mean pattern f , (b) Sample of 10 curves out of $n = 200$, (c) Direct mean, (d) Empirical wavelet coefficients after deconvolution (ordered for small to large resolution levels) and value of the threshold, (e) Deconvolution by wavelet thresholding, (f) Procrustean mean




Figure 2: HeaviSine function. (a) Mean pattern f , (b) Sample of 10 curves out of $n = 200$, (c) Direct mean, (d) Empirical wavelet coefficients after deconvolution (ordered for small to large resolution levels) and value of the threshold, (e) Deconvolution by wavelet thresholding, (f) Procrustean mean

6.2 Estimation when the γ_ℓ 's are known

Now, consider the step function shown in Figure 5a and let us take for g the density displayed in Figure 5b that is a mixture of two Laplace distributions with different means. Estimation by wavelet thresholding is quite satisfactory except the pseudo-gibbs phenomena at the discontinuity points of f , which could be reduced by using a translation invariant wavelet decomposition.




Figure 3: Blocks function. (a) Mean pattern f , (b) Sample of 10 curves out of $n = 200$, (c) Direct mean, (d) Empirical wavelet coefficients after deconvolution (ordered for small to large resolution levels) and value of the threshold, (e) Deconvolution by wavelet thresholding, (f) Procrustean mean




Figure 4: Doppler function. (a) Mean pattern f , (b) Sample of 10 curves out of $n = 200$, (c) Direct mean, (d) Empirical wavelet coefficients after deconvolution (ordered for small to large resolution levels) and value of the threshold, (e) Deconvolution by wavelet thresholding, (f) Procrustean mean

The Procrustean mean is not very satisfactory as it is composed of two step functions (for a fair comparison the estimated shifts at iteration $i_{\max} = 3$ have been centered at the true mean of the density g). Note that the iterative procedure used to compute the Procrustean mean is initialized with the direct mean f_0 which is a very poor estimation for f as it is the sum of two step functions with different amplitude. Hence, this makes the Procrustean mean a non-consistent procedure for the estimation of f , which somewhat illustrates the crucial dependence on the initialization step of such an iterative method.

7 Conclusions and future work

This paper makes a connection between mean pattern estimation and the statistical analysis of inverse problems for a very simple model with shifted curves. A natural extension would be to consider more complex deformations such as the homothetic shifted regression model proposed in [33], or the rigid deformation model for images considered in [4].

Another promising approach to estimate a mean pattern would be to take a Bayesian point of view, and then to estimate the common shape via the EM algorithm where the unobserved random shifts are considered as hidden variables. Such an approach has been proposed in [1]




Figure 5: Step function. (a) Mean pattern f , (b) Density g of the shifts, (c) Direct mean, (d) Empirical wavelet coefficients ordered for small to large resolution levels, and value of the threshold, (e) Deconvolution by wavelet thresholding, (f) Procrustean mean centered at the true mean of the shifts

to compute the mean pattern of a set of images. However the approach followed in [1] has not been shown to be consistent from a nonparametric point of view. Moreover, optimality of such a Bayesian procedure remains to be studied.

A Appendix section

In what follows C will denote a generic constant whose value may change from line to line.

Proof of Theorem 1.1: it follows immediately from Theorem 3.1 and Theorem 4.1. $\square$

Proof of Proposition 2.1: let $\kappa_\ell = \left(\frac{\tilde{\gamma}_\ell}{\gamma_\ell} - 1\right) \theta_\ell$ and $\epsilon_{\ell,n} = \frac{\epsilon}{\gamma_\ell} \left(\frac{1}{n} \sum_{m=1}^n z_{\ell,m}\right)$ for all $\ell \in \mathbb{Z}$. Then, for a given filter λ , the risk $\mathcal{R}(\hat{f}_{n,\lambda}, f)$ can be written as

$$\begin{aligned} \mathcal{R}(\hat{f}_{n,\lambda}, f) &= \sum_{\ell \in \mathbb{Z}} (\lambda_\ell - 1)^2 \theta_\ell^2 + \mathbb{E} [\lambda_\ell^2 |\kappa_\ell|^2 + \lambda_\ell^2 |\epsilon_{\ell,n}|^2] + \lambda_\ell (\lambda_\ell - 1) \mathbb{E} [\bar{\theta}_\ell \kappa_\ell + \theta_\ell \bar{\kappa}_\ell] \\ &\quad + \lambda_\ell (\lambda_\ell - 1) \mathbb{E} [\theta_\ell \bar{\epsilon}_{\ell,n} + \bar{\theta}_\ell \epsilon_{\ell,n}] + \lambda_\ell^2 \mathbb{E} [\bar{\kappa}_\ell \epsilon_{\ell,n} + \kappa_\ell \bar{\epsilon}_{\ell,n}]. \end{aligned}$$

Now using the fact that κ_ℓ and $\epsilon_{\ell,n}$ are independent and that $\mathbb{E} \epsilon_{\ell,n} = 0$, we obtain that

$$\begin{aligned} R(\hat{f}_{n,\lambda}, f) &= \sum_{\ell \in \mathbb{Z}} \left[(\lambda_\ell - 1)^2 |\theta_\ell|^2 + \lambda_\ell^2 |\theta_\ell|^2 \mathbb{E} \left| \frac{\tilde{\gamma}_\ell}{\gamma_\ell} - 1 \right|^2 + \frac{\lambda_\ell^2 \epsilon^2}{n |\gamma_\ell|^2} \right] \\ &= \sum_{\ell \in \mathbb{Z}} (\lambda_\ell - 1)^2 |\theta_\ell|^2 + \sum_{\ell \in \mathbb{Z}} \lambda_\ell^2 |\theta_\ell|^2 \left(\frac{1}{|\gamma_\ell|^2} \left(\frac{1}{n} + \frac{n-1}{n} \gamma_\ell \gamma_{-\ell} \right) - 1 \right) \\ &\quad + \sum_{\ell \in \mathbb{Z}} \frac{\lambda_\ell^2 \epsilon^2}{n |\gamma_\ell|^2} \\ &= \sum_{\ell \in \mathbb{Z}} (\lambda_\ell - 1)^2 |\theta_\ell|^2 + \sum_{\ell \in \mathbb{Z}} \frac{\lambda_\ell^2}{n} \left[|\theta_\ell|^2 \left(\frac{1}{|\gamma_\ell|^2} - 1 \right) + \frac{\epsilon^2}{|\gamma_\ell|^2} \right], \end{aligned}$$

which completes the proof. $\square$

Proof of Proposition 2.2: from Proposition 2.1 it follows that

$$\mathcal{R}(\hat{f}_{n,\lambda^M}, f) = \sum_{|\ell| > M_n} |\theta_\ell|^2 + \frac{1}{n} \sum_{|\ell| \leq M_n} \left(|\theta_\ell|^2 \left(\frac{1}{|\gamma_\ell|^2} - 1 \right) + \frac{\epsilon^2}{|\gamma_\ell|^2} \right)$$

By assumption $f \in H_s(A)$, which implies that there exists two positive constants C_1 and C_2 not depending on f and n such that for all sufficiently large n , $\sum_{|\ell| > M_n} |\theta_\ell|^2 \leq C_1 M_n^{-2s}$ and $\frac{1}{n} \sum_{|\ell| \leq M_n} |\theta_\ell|^2 \leq C_2 n^{-1}$. Now, given that g satisfies Assumption (1.1), it follows that there exists a positive constants C_3 not depending on f and n such that for all sufficiently large n , $\frac{1}{n} \sum_{|\ell| \leq M_n} \frac{|\theta_\ell|^2 + \epsilon^2}{|\gamma_\ell|^2} \leq C_3 n^{-1} M_n^{2\nu+1}$. Hence the result immediately follows from the choice $M_n \sim n^{\frac{1}{2s+2\nu+1}}$, which completes the proof. $\square$

For the proof of Propositions 3.1 and 3.2, let us remark that that $\hat{\beta}_{j,k} - \beta_{j,k} = Z_1 + Z_2$ with

$$Z_1 = \sum_{\ell \in \Omega_j} \psi_\ell^{j,k} \theta_\ell \left(\frac{\tilde{\gamma}_\ell}{\gamma_\ell} - 1 \right) \quad \text{and} \quad Z_2 = \epsilon \sum_{\ell \in \Omega_j} \frac{\psi_\ell^{j,k}}{\gamma_\ell} \eta_\ell. \quad (\text{A.1})$$

Under Assumption 3.1, $G(x) = \sum_{m \in \mathbb{Z}} g(x+m)$, exists for all $x \in [0, 1]$ and is a bounded density. Throughout the proof we use the following lemma whose proof is straightforward:

Lemma A.1 *Let $h \in L^2([0, 1])$ be a 1-periodic function on $\mathbb{R}$. Then, $\int_{\mathbb{R}} h(x)g(x)dx = \int_0^1 h(x)G(x)dx$.*

Proof of Proposition 3.1: first note that since $|\psi_\ell^{j,k}| \leq 2^{-j/2}$ and $\Omega_j \subset [-2^{j+2}c_0, -2^j c_0] \cup [2^j c_0, 2^{j+2}c_0]$, see [17], it follows that $\#\{\Omega_j\} \leq 4\pi 2^j$ and that under Assumption 1.1, $|\gamma_\ell|^{-2} \sim 2^{2j\nu}$ for all $\ell \in \Omega_j$. This implies that there exists a constant $C > 0$ such that

$$\sum_{\ell \in \Omega_j} \left| \frac{\psi_\ell^{j,k}}{\gamma_\ell} \right|^2 \leq C 2^{2j\nu} \quad \text{and} \quad \sum_{\ell \in \Omega_j} \left| \frac{\psi_\ell^{j,k}}{\gamma_\ell} \right| \leq C 2^{j(\nu+1/2)}. \quad (\text{A.2})$$

Then, we need the following lemma which shows that the Fourier coefficients $\theta_\ell = \int_0^1 e^{-2i\ell\pi x} f(x)dx$ are uniformly bounded for all $f \in B_{p,q}^s(A)$.

Lemma A.2 *Let $1 \leq p \leq \infty$, $1 \leq q \leq \infty$, $s - 1/p + 1/2 > 0$ and $A > 0$. Then, there exists a constant $A' > 0$ such that for all $f \in B_{p,q}^s(A)$ and all $\ell \in \mathbb{Z}$, $|\theta_\ell| \leq A'$.*

Proof: since $|\phi_\ell^{j_0,k}| \leq 2^{-j_0/2}$ and $|\psi_\ell^{j,k}| \leq 2^{-j/2}$ one can remark using Cauchy-Schwarz inequality that for any $j_0 \geq 0$

$$\begin{aligned} |\theta_\ell| &\leq \sum_{k=0}^{2^{j_0}-1} |c_{j_0,k}| |\phi_\ell^{j_0,k}| + \sum_{j=j_0}^{+\infty} \sum_{k=0}^{2^j-1} |\beta_{j,k}| |\psi_\ell^{j,k}| \\ &\leq \left(\sum_{k=0}^{2^{j_0}-1} |c_{j_0,k}|^2 \right)^{1/2} + \sum_{j=j_0}^{+\infty} \left(\sum_{k=0}^{2^j-1} |\beta_{j,k}|^2 \right)^{1/2} \end{aligned}$$

Now using the inequality $(\sum_{r=1}^m |a_r|^2)^{1/2} \leq m^{(1/2-1/p)+} (\sum_{r=1}^m |a_r|^p)^{1/p}$ for ℓ_p -norm in $\mathbb{R}^m$ it follows that $|\theta_\ell| \leq 2^{j_0(1/2-1/p)+} \left(\sum_{k=0}^{2^{j_0}-1} |c_{j_0,k}|^p \right)^{1/p} + \sum_{j=j_0}^{+\infty} 2^{j(1/2-1/p)+} \left(\sum_{k=0}^{2^j-1} |\beta_{j,k}|^p \right)^{1/p}$.

Since $f \in B_{p,q}^s(A)$, one has that $\left(\sum_{k=0}^{2^j-1} |\beta_{j,k}|^p \right)^{1/p} \leq A 2^{-j(s+1/2-1/p)}$ and $\left(\sum_{k=0}^{2^{j_0}-1} |c_{j_0,k}|^p \right)^{1/p} \leq A$ which implies that $|\theta_\ell| \leq A 2^{j_0(1/2-1/p)+} + A \sum_{j=j_0}^{+\infty} 2^{-j(s+1/2-1/p-(1/2-1/p)+)}$. Taking for instance $j_0 = 0$ completes the proof since by assumption $s + 1/2 - 1/p > 0$. $\square$

Control of $\mathbb{E}|\hat{\beta}_{j,k} - \beta_{j,k}|^2$ (the proof to control $\mathbb{E}|\hat{c}_{j_0,k} - c_{j_0,k}|^2$ follows from the same arguments): from the decomposition (A.1) it follows that $\mathbb{E}|\hat{\beta}_{j,k} - \beta_{j,k}|^2 \leq 2\mathbb{E}|Z_1|^2 + 2\mathbb{E}|Z_2|^2$. Since η_ℓ are iid $N_{\mathbb{C}}(0, 1/n)$, the bound (A.2) implies that

$$\mathbb{E}|Z_2|^2 \leq C \frac{2^{2j\nu}}{n}. \quad (\text{A.3})$$

Then, let us write $Z_1 = \frac{1}{n} \sum_{m=1}^n (W_m - \mathbb{E}W_m)$ with $W_m = h_{j,k}(\tau_m)$ and $h_{j,k}(\tau) = \sum_{\ell \in \Omega_j} \frac{\psi_\ell^{j,k} \theta_\ell}{\gamma_\ell} e^{-i2\pi\ell\tau}$ for $\tau \in \mathbb{R}$. By independence of the τ_m 's, one has that $\mathbb{E}|Z_1|^2 \leq \frac{1}{n} \mathbb{E}|W_1|^2$. Applying Lemma A.1 with $h = h_{j,k}$ and since the density G is bounded, it follows that

$$\begin{aligned} \mathbb{E}|W_1|^2 &= \int_{\mathbb{R}} |h_{j,k}(\tau)|^2 g(\tau) d\tau = \int_0^1 |h_{j,k}(\tau)|^2 G(\tau) d\tau \\ &\leq C \int_0^1 |h_{j,k}(\tau)|^2 d\tau \leq C \sum_{\ell \in \Omega_j} \frac{|\psi_\ell^{j,k}|^2 |\theta_\ell|^2}{|\gamma_\ell|^2} \end{aligned} \quad (\text{A.4})$$

where the last inequality follows from Parseval's relation. Then, using the bound (A.2) and Lemma A.2, inequality (A.4) implies that there exists a constant C such that for all $f \in B_{p,q}^s(A)$

$$\mathbb{E}Z_1^2 \leq C \frac{1}{n} \sum_{\ell \in \Omega_j} \frac{|\psi_\ell^{j,k}|^2}{|\gamma_\ell|^2} \leq C \frac{2^{2j\nu}}{n}, \quad (\text{A.5})$$

Hence using the bounds (A.3) and (A.5), it follows that there exists a constant C such that for all $f \in B_{p,q}^s(A)$, $\mathbb{E}|\hat{\beta}_{j,k} - \beta_{j,k}|^2 \leq C \frac{2^{2j\nu}}{n}$.

Control of $\mathbb{E}|\hat{\beta}_{j,k} - \beta_{j,k}|^4$: from the decomposition (A.1) it follows that $\mathbb{E}|\hat{\beta}_{j,k} - \beta_{j,k}|^4 \leq C(\mathbb{E}|Z_1|^4 + \mathbb{E}|Z_2|^4)$. As Z_2 is a centered Gaussian variable with variance $\frac{1}{n} \epsilon^2 \sum_{\ell \in \Omega_j} |\frac{\psi_\ell^{j,k}}{\gamma_\ell}|^2 \leq C \frac{2^{2j\nu}}{n}$, one has that

$$\mathbb{E}|Z_2|^4 \leq C \frac{2^{4j\nu}}{n^2}. \quad (\text{A.6})$$

Then, remark that $Z_1 = \frac{1}{n} \sum_{m=1}^n Y_m$ with $Y_m = \sum_{\ell \in \Omega_j} \frac{\psi_\ell^{j,k} \theta_\ell}{\gamma_\ell} (e^{-i2\pi\ell\tau_m} - \gamma_\ell)$, and recall the so-called Rosenthal's inequality for moment bounds of iid variables [32]: if $X_1, \dots, X_n$ are iid random variables such that $\mathbb{E}X_j = 0$, $\mathbb{E}X_j^2 \leq \sigma^2$, there exists a positive constant C such that $\mathbb{E}|\sum_{j=1}^n X_j/n|^4 \leq C(\sigma^4/n^2 + \mathbb{E}|X_1|^4/n^3)$.

Now remark that $\mathbb{E}Y_m = 0$, and arguing as previously for the control of $\mathbb{E}|W_1|^2$, see equation (A.4), it follows that $\mathbb{E}|Y_m|^2 \leq C 2^{2j\nu}$ where C is constant not depending on f . Then, remark that

$$\mathbb{E}|Y_1|^4 \leq C \left(\int_{\mathbb{R}} |h_{j,k}(\tau)|^4 g(\tau) d\tau + |\beta_{j,k}|^4 \right) \text{ with } h_{j,k}(\tau) = \sum_{\ell \in \Omega_j} \frac{\psi_\ell^{j,k} \theta_\ell}{\gamma_\ell} e^{-i2\pi\ell\tau},$$

and that

$$\int_{\mathbb{R}} |h_{j,k}(\tau)|^4 g(\tau) d\tau \leq \sup_{\tau \in \mathbb{R}} \{|h_{j,k}(\tau)|^2\} \int_{\mathbb{R}} |h_{j,k}(\tau)|^2 g(\tau) d\tau$$

Note that using (A.2) and Lemma A.2, it follows that $|h_{j,k}(\tau)| \leq \sum_{\ell \in \Omega_j} \frac{|\psi_\ell^{j,k}| |\theta_\ell|}{|\gamma_\ell|} \leq C \sum_{\ell \in \Omega_j} \frac{|\psi_\ell^{j,k}|}{|\gamma_\ell|} \leq C 2^{j(\nu+1/2)}$ uniformly for $f \in B_{p,q}^s(A)$. Then, arguing as for the control of $\mathbb{E}|W_1|^2$, see equation (A.4), one has that $\int_{\mathbb{R}} |h_{j,k}(\tau)|^2 g(\tau) d\tau \leq C 2^{2j\nu}$, which finally implies that $\mathbb{E}|Y_1|^4 \leq C 2^{4j\nu}$, since $|\beta_{j,k}| \leq C$ uniformly for $f \in B_{p,q}^s(A)$. Then, using Rosenthal's inequality, it follows that there exists a constant C such that for all $f \in B_{p,q}^s(A)$

$$\mathbb{E}|Z_1|^4 \leq C \left(\frac{2^{4j\nu}}{n^2} + \frac{2^{j(4\nu+1)}}{n^3} \right), \quad (\text{A.7})$$

which completes the proof for the control of $\mathbb{E}|\hat{\beta}_{j,k} - \beta_{j,k}|^4$ using (A.6) and (A.7). $\square$

Proof of Proposition 3.2: let $u > 0$, and remark that from the decomposition (A.1) it follows

$$\mathbb{P}(|\hat{\beta}_{j,k} - \beta_{j,k}| \geq u) \leq \mathbb{P}(|Z_1| \geq u/2) + \mathbb{P}(|Z_2| \geq u/2)$$

Recall that the η_ℓ 's are iid $N_{\mathbb{C}}(0, 1/n)$. Hence, Z_2 is a centered Gaussian variable with variance $\frac{1}{n}\epsilon^2 \sum_{\ell \in \Omega_j} \left| \frac{\psi_\ell^{j,k}}{\gamma_\ell} \right|^2 \leq \frac{1}{n}\sigma_j^2$, with $\sigma_j^2 = 2^{-j}\epsilon^2 \sum_{\ell \in \Omega_j} |\gamma_\ell|^{-2}$, which implies that (see e.g. [25]) for any $t > 0$

$$\mathbb{P}(|Z_2| \geq \sigma_j \sqrt{\frac{2t}{n}}) \leq 2 \exp(-t) \quad (\text{A.8})$$

By definition, $\tilde{\gamma}_\ell = \frac{1}{n} \sum_{m=1}^n e^{-i2\pi\ell\tau_m}$, and thus $Z_1 = \frac{1}{n} \sum_{m=1}^n (W_m - \mathbb{E}W_m)$ with $W_m = \sum_{\ell \in \Omega_j} \frac{\psi_\ell^{j,k}\theta_\ell}{\gamma_\ell} e^{-i2\pi\ell\tau_m}$. Remark that W_m are random variables bounded by $\delta_j = 2^{-j/2} \sum_{\ell \in \Omega_j} \frac{|\theta_\ell|}{|\gamma_\ell|}$. Moreover, using Lemma A.1 with $h = h_{j,k}(\tau) = \sum_{\ell \in \Omega_j} \frac{\psi_\ell^{j,k}\theta_\ell}{\gamma_\ell} e^{-i2\pi\ell\tau}$ for $\tau \in \mathbb{R}$ it follows that

$$\mathbb{E}|W_1|^2 = \int_{\mathbb{R}} |h_{j,k}(\tau)|^2 g(\tau) d\tau \leq \|g\|_\infty \sum_{\ell \in C_j} \frac{|\psi_\ell^{j,k}|^2 |\theta_\ell|^2}{|\gamma_\ell|^2} \leq V_j^2,$$

where $V_j^2 = \|g\|_\infty 2^{-j} \sum_{\ell \in C_j} \frac{|\theta_\ell|^2}{|\gamma_\ell|^2}$, since $|\psi_\ell^{j,k}| \leq 2^{-j/2}$ and $\|g\|_\infty = \|G\|_\infty$. Hence, from Bernstein's inequality it follows that for any $t > 0$ (see e.g. Proposition 2.9 in [25])

$$\mathbb{P} \left(|Z_1| \geq \sqrt{\frac{2V_j^2 t}{n}} + \delta_j \frac{t}{3n} \right) \leq 2 \exp(-t). \quad (\text{A.9})$$

Taking $u = 2 \max \left(\sigma_j \sqrt{\frac{2t}{n}}, \sqrt{\frac{2V_j^2 t}{n}} + \delta_j \frac{t}{3n} \right)$ for $t > 0$ concludes the proof of Proposition 3.2. $\square$

Proof of Lemma 3.1: let $Z = \sqrt{|\hat{\theta}|_\ell^2 + \epsilon^2} = \sqrt{\frac{1}{n} \sum_{m=1}^n |c_{m,\ell}|^2}$ and recall that $c_{m,\ell} = \theta_\ell e^{-i2\pi\ell\tau_m} + \epsilon z_{\ell,m}$. As the $z_{\ell,m}$'s are iid standard complex Gaussian variables, by conditioning with respect to $\tau_1, \dots, \tau_n$ and by using a concentration inequality for Lipschitz functions of random variables (see e.g. [25]), one has that for any $t > 0$

$$\mathbb{P} \left(Z > \mathbb{E}Z + \epsilon \sqrt{\frac{2t}{n}} \right) \leq \exp(-t) \text{ and } \mathbb{P} \left(Z < \mathbb{E}Z - \epsilon \sqrt{\frac{2t}{n}} \right) \leq \exp(-t). \quad (\text{A.10})$$

By Jensen's inequality and using the concavity of the function $x \mapsto \sqrt{x}$, one has that

$$\mathbb{E}Z \leq \left(\frac{1}{n} \sum_{m=1}^n \mathbb{E}|c_{m,\ell}|^2 \right)^{1/2} = (|\theta_\ell|^2 + \epsilon^2)^{1/2} \leq |\theta_\ell| + \epsilon.$$

Hence, the above inequality and (A.10) imply that $\mathbb{P} \left(Z > |\theta_\ell| + \epsilon + \epsilon \sqrt{\frac{2t}{n}} \right) \leq \exp(-t)$. Using the concavity of the function $x \mapsto \sqrt{x}$ and then the convexity of the function $x \mapsto |x|$ it follows that $\mathbb{E}Z = \mathbb{E} \sqrt{\frac{1}{n} \sum_{m=1}^n |c_{m,\ell}|^2} \geq \frac{1}{n} \sum_{m=1}^n \mathbb{E}|c_{m,\ell}| \geq \frac{1}{n} \sum_{m=1}^n |\mathbb{E}c_{m,\ell}| = |\theta_\ell|$. Hence, $\mathbb{E}Z \geq |\theta_\ell|$ and thus using (A.10), this implies that $\mathbb{P} \left(Z < |\theta_\ell| - \epsilon \sqrt{\frac{2t}{n}} \right) \leq \exp(-t)$, which completes the proof of Lemma 3.1. $\square$

Proof of Proposition 3.3: from Lemma 3.1 and the definition of $|\tilde{\theta}_\ell|$, it immediately follows that for any $\ell \in \Omega_j$

$$\mathbb{P} \left(|\theta_\ell| > |\tilde{\theta}_\ell| \right) \leq C 2^{-j} n^{-2}. \quad (\text{A.11})$$

Now remark that by definition of λ_j and λ_j^*

$$\begin{aligned}
\mathbb{P}\left(|\hat{\beta}_{j,k} - \beta_{j,k}| \geq \lambda_j\right) &= \mathbb{P}\left(|\hat{\beta}_{j,k} - \beta_{j,k}| \geq \lambda_j; \forall \ell \in \Omega_j, |\theta_\ell| \leq |\tilde{\theta}_\ell|\right) \\
&\quad + \mathbb{P}\left(|\hat{\beta}_{j,k} - \beta_{j,k}| \geq \lambda_j; \exists \ell \in \Omega_j, |\theta_\ell| > |\tilde{\theta}_\ell|\right) \\
&\leq \mathbb{P}\left(|\hat{\beta}_{j,k} - \beta_{j,k}| \geq \lambda_j^*\right) + \sum_{\ell \in \Omega_j} \mathbb{P}\left(|\theta_\ell| > |\tilde{\theta}_\ell|\right) \\
&\leq C(n^{-2} + \#\{\Omega_j\}2^{-j}n^{-2}) \leq Cn^{-2},
\end{aligned}$$

where the last inequality follows from Proposition 3.2, inequality (A.11) and the fact that $\#\{\Omega_j\} \leq C2^j$, which completes the proof of Proposition 3.3 $\square$

A.1 Proof of Theorem 3.1

Under the assumptions of Theorem 3.1 one can remark that Proposition 3.1 and Proposition 3.3 imply that the conditions (3.4), (3.5) and (3.6) are satisfied. Consider the event $\mathcal{A} = \{\forall \ell \in \Omega_j, |\tilde{\theta}_\ell| \leq |\theta_\ell| + \epsilon + 2\frac{2\log(n^{2^{2j}})}{n}\}$. From the bound (A.1), and the definition of λ_j and λ_j^* , one can easily check that on the event $\mathcal{A}$

$$\lambda_j \leq C2^{j\nu} \sqrt{\frac{2\log(n)}{n}},$$

where C is a uniform constant not depending on f . Using Lemma 3.1, one has that $\mathbb{P}(\mathcal{A}) \geq 1 - n^{-2}$, and thus it follows from the above inequality that the random threshold λ_j satisfies the condition (3.7) except on a set of probability less than n^{-2} . Hence the results follows using the arguments in the proof of Theorem 1 in [17]. $\square$

A.2 Proof of Theorem 4.1

Let us fix a resolution $j \geq 0$ whose choice will be discussed later on, and consider for any $\eta = (\eta_i)_{i \in \{0 \dots 2^j-1\}} \in \{\pm 1\}^{2^j}$ the function $f_{j,\eta}$ defined as $f_{j,\eta} = \gamma_j \sum_{i=0}^{2^j-1} \eta_i \psi_{j,k}$, where $\gamma_j = c2^{-j(s+1/2)}$, and c is a positive constant satisfying $c \leq A$ which implies that $f_{j,\eta} \in B_{p,q}^s(A)$. For some $0 \leq i \leq 2^j - 1$ and $\eta \in \{\pm 1\}^{2^j}$, define also the vector $\eta^i \in \{\pm 1\}^{2^j}$ with components equal to those of η except the i^{th} one.

Let $\psi_{j,k} \star g(x) = \int_{\mathbb{R}} \psi_{j,k}(x-u)g(u)du$. By Parseval's relation, one has that $\|\psi_{j,k} \star g\|^2 = \sum_{\ell \in \Omega_j} |\psi_\ell^{j,k}|^2 |\gamma_\ell|^2$. Hence, under Assumption 1.1 of a polynomial decay for γ_ℓ and using the fact that $|\psi_\ell^{j,k}| \leq 2^{-j/2}$ for Meyer wavelets (see [17]) it follows that there exists a constant C such that $\|\psi_{j,k} \star g\|^2 \leq C2^{-2j\nu}$.

A.2.1 Algebraic settings

We set the resolution $j = j(n)$ to be the largest integer satisfying $2^{j(n)} \leq n^{\frac{1}{2s+2\nu+1}}$. However, to simplify the presentation, the dependency of j on n is dropped in what follows. The definition of $f_{j,\eta}$, γ_j and the bound $\|\psi_{j,k} \star g\|^2 \leq C2^{-2j\nu}$ thus imply that

$$\begin{aligned}
\gamma_j &= \mathcal{O}(n^{-\frac{s+1/2}{2s+2\nu+1}}) \text{ and } \|f_{j,\eta}\|^2 = \mathcal{O}(n^{-\frac{2s}{2s+2\nu+1}}), \\
\|f_{j,\eta} \star g\|^2 &= \|\gamma_j \sum_k \eta_k (\psi_{j,k} \star g)\|^2 = \mathcal{O}\left(n^{\frac{-2s-2\nu}{2s+2\nu+1}}\right), \\
\|(f_{j,\eta} - f_{j,\eta^i}) \star g\|^2 &= \|2\gamma_j \eta_i (\psi_{j,i} \star g)\|^2 = \mathcal{O}(\gamma_j^2 2^{-2j\nu}) = \mathcal{O}(n^{-1}).
\end{aligned}$$

From the above equations, we can thus conclude that $n\|(f_{j,\eta} - f_{j,\eta^i}) \star g\|^2 = \mathcal{O}(1)$, but note that the term $n\|f_{j,\eta} \star g\|^2$ does not converge to 0. At last, observe that by assumption $s > 2\nu + 1$ which implies that $n\|f_{j,\eta} \star g\|^3 \rightarrow 0$, $n\|(f_{j,\eta} - f_{j,\eta^i}) \star g\| \|f_{j,\eta}\| \|f_{j,\eta} \star g\| \rightarrow 0$ and $n\|f_{j,\eta}\|^3 \rightarrow 0$.

A.2.2 Likelihood ratio

Let $F(Y)$ be real valued and bounded measurable function of the n trajectories $Y = (Y_1, \dots, Y_n)$. Because of the independence of the τ_i 's and the W_i 's, we have that

$$\mathbb{E}_f [F(Y)] = \int_{\mathbb{R}^n} \mathbb{E}_{f,W} [F(Y) | \tau_1 = t_1, \dots, \tau_n = t_n] g(t_1) dt_1 \dots g(t_n) dt_n,$$

where $\mathbb{E}_f$ denotes the expectation with respect to the law of $Y = (Y_1, \dots, Y_n)$ when f is the true hypothesis, and $\mathbb{E}_{f,W}$ is used to denote expectation only with respect to law of the Brownian motions $W_1, \dots, W_n$ where the shifts are fixed and f is the true hypothesis. Now using the classical Girsanov formula it follows that for any function $h \in L^2([0, 1])$

$$\begin{aligned} \mathbb{E}_f [F(Y)] &= \int_{\mathbb{R}^n} \mathbb{E}_{h,W} [F(Y) | \tau_1 = t_1, \dots, \tau_n = t_n] \Lambda_n(f, h) g(t_1) dt_1 \dots g(t_n) dt_n \\ &= \mathbb{E}_h [F(Y) \Lambda_n(f, h)] \end{aligned}$$

where $\Lambda_n(f, h)$ is the following likelihood ratio

$$\Lambda_n(f, h) = \prod_{i=1}^n \exp \left(\int_0^1 (f(x - \tau_i) - h(x - \tau_i)) dY_i(x) + \frac{1}{2} \|h\|^2 - \frac{1}{2} \|f\|^2 \right).$$

In what follows, f_0 is used to denote the hypothesis $f \equiv 0$.

A.2.3 Technical Lemmas

Given n arbitrary trajectories $Y_1, \dots, Y_n$ from model (1.1), we define $\mathbb{E}_\tau (\Lambda_n(f_{j,\eta^i}, f_0))$ as the expectation of the likelihood ratio with respect to the law of the random shifts, namely

$$\begin{aligned} \mathbb{E}_\tau (\Lambda_n(f_{j,\eta^i}, f_0)) &= \int_{\mathbb{R}^n} \prod_{i=1}^n e^{\int_0^1 (f(x - \tau_i) - h(x - \tau_i)) dY_i(x) + \frac{1}{2} \|h\|^2 - \frac{1}{2} \|f\|^2} \\ &\quad g(\tau_1) \dots g(\tau_n) d\tau_1 \dots d\tau_n. \end{aligned}$$

Lemma A.3 Suppose for some constants $\lambda > 0$ and $\pi_0 > 0$ and all sufficiently large n we have that

$$\mathbb{P}_{f_{j,\eta}} \left(\frac{\mathbb{E}_\tau (\Lambda_n(f_{j,\eta^i}, f_0))}{\mathbb{E}_\tau (\Lambda_n(f_{j,\eta}, f_0))} \geq e^{-\lambda} \right) \geq \pi_0, \quad (\text{A.12})$$

for all $f_{j,\eta}$ and all $i \in \{0 \dots 2^j - 1\}$. Then, there exists a positive constant C , such that for all sufficiently large n and any estimator $\hat{f}_n$

$$\max_{\eta \in \{\pm 1\}^{2^j}} \mathbb{E}_{f_{j,\eta}} \|\hat{f}_n - f_{j,\eta}\|^2 \geq C \pi_0 e^{-\lambda} 2^j \gamma_j^2$$

Proof of Lemma A.3 : our proof is inspired by the proof of Lemma 2.10 in [14]. For this let $I_{jk} = [\frac{k}{2^j}, \frac{k+1}{2^j}]$ and arguing as in [14] it follows that for any estimator $\hat{f}_n$

$$\begin{aligned} \max_{\eta \in \{\pm 1\}^{2^j}} \mathbb{E}_{f_{j,\eta}} \|\hat{f}_n - f_{j,\eta}\|^2 &\geq 2^{-2^j} \sum_{k=0}^{2^j-1} \sum_{\eta | \eta_k = 1} \mathbb{E}_{f_{j,\eta}} \left[\int_{I_{j,k}} |\hat{f}_n - f_{j,\eta}|^2 \right. \\ &\quad \left. + \Lambda_n(f_{j,\eta^k}, f_{j,\eta}) \int_{I_{j,k}} |\hat{f}_n - f_{j,\eta^k}|^2 \right]. \end{aligned}$$

Let $Z(Y) = \left[\int_{I_{j,k}} |\hat{f}_n - f_{j,\eta}|^2 + \Lambda_n(f_{j,\eta^k}, f_{j,\eta}) \int_{I_{j,k}} |\hat{f}_n - f_{j,\eta^k}|^2 \right]$ and remark that

$$\begin{aligned} \mathbb{E}_{f_{j,\eta}}[Z(Y)] &= \mathbb{E}_{f_0, W} \int_{\mathbb{R}^n} \left[\Lambda_n(f_{j,\eta}, f_0) \int_{I_{j,k}} |\hat{f}_n - f_{j,\eta}|^2 \right. \\ &\quad \left. + \Lambda_n(f_{j,\eta^k}, f_0) \int_{I_{j,k}} |\hat{f}_n - f_{j,\eta^k}|^2 \right] g(\tau_1) d\tau_1 \dots g(\tau_n) d\tau_n. \end{aligned}$$

Now, since under the hypothesis f_0 the trajectories $Y_1, \dots, Y_n$ do not depend on the random shifts $\tau_1, \dots, \tau_n$ it follows that $\hat{f}_n$ does not depend on the shifts $\tau_1, \dots, \tau_n$ as it is by definition a measurable function with respect to the sigma algebra generated by $Y_1, \dots, Y_n$. This implies that for any $\delta > 0$

$$\begin{aligned} \mathbb{E}_{f_{j,\eta}}[Z(Y)] &= \mathbb{E}_{f_0, W} \left[\mathbb{E}_\tau (\Lambda_n(f_{j,\eta}, f_0)) \int_{I_{j,k}} |\hat{f}_n - f_{j,\eta}|^2 \right. \\ &\quad \left. + \mathbb{E}_\tau (\Lambda_n(f_{j,\eta^k}, f_0)) \int_{I_{j,k}} |\hat{f}_n - f_{j,\eta^k}|^2 \right] \\ &\geq \mathbb{E}_{f_0, W} \left[\mathbb{E}_\tau (\Lambda_n(f_{j,\eta}, f_0)) \delta^2 \mathbb{1}_{\left\{ \int_{I_{j,k}} |\hat{f}_n - f_{j,\eta}|^2 > \delta^2 \right\}} \right. \\ &\quad \left. + \mathbb{E}_\tau (\Lambda_n(f_{j,\eta^k}, f_0)) \delta^2 \mathbb{1}_{\left\{ \int_{I_{j,k}} |\hat{f}_n - f_{j,\eta^k}|^2 > \delta^2 \right\}} \right]. \end{aligned}$$

Now, remark that

$$\begin{aligned} \left(\int_{I_{j,k}} |\hat{f}_n - f_{j,\eta}|^2 \right)^{1/2} + \left(\int_{I_{j,k}} |\hat{f}_n - f_{j,\eta^k}|^2 \right)^{1/2} &\geq \left(\int_{I_{j,k}} |f_{j,\eta} - f_{j,\eta^k}|^2 \right)^{1/2} \\ &\geq 2\gamma_j \left(\int_{I_{j,k}} |\psi_{jk}|^2 \right)^{1/2}, \end{aligned}$$

and let us argue as in the proof of Lemma 2 in [35] to find a lower bound for $\int_{I_{j,k}} |\psi_{jk}|^2$. By definition, see Section 3, $\psi_{j,k}(x) = 2^{j/2} \sum_{i \in \mathbb{Z}} \psi^*(2^j(x+i) - k)$ where ψ^* is the Meyer wavelet over $\mathbb{R}$ used to construct ψ . A change of variable shows that $\int_{I_{j,k}} |\psi_{jk}(x)|^2 dx = \int_0^1 |\sum_{i \in \mathbb{Z}} \psi^*(x + 2^j i)|^2 dx$ which implies that $\int_{I_{j,k}} |\psi_{jk}(x)|^2 dx \geq \int_0^1 |\psi^*(x)|^2 dx - \sum_{i \in \mathbb{Z}^*} \int_0^1 |\psi^*(x + 2^j i)|^2 dx$. Now as ψ^* has a fast decay, it follows that there exists a constant $A > 0$ such that $|\psi^*(x)| \leq \frac{A}{1+x^2}$. Thus, $\int_{I_{j,k}} |\psi_{jk}(x)|^2 dx \geq \int_0^1 |\psi^*(x)|^2 dx - A^2 2^{-2j} \sum_{i \in \mathbb{Z}^*} i^{-2}$. Hence, it follows that there exists a constant $\rho > 0$ such that $\left(\int_{I_{j,k}} |\psi_{jk}|^2 \right)^{1/2} \geq \rho$ for any k , and all j sufficiently large.

Hence if one takes $\delta = 2\rho\gamma_j$ it follows that

$$\mathbb{1}_{\left\{ \int_{I_{j,k}} |\hat{f}_n - f_{j,\eta}|^2 > \delta^2 \right\}} \geq \mathbb{1}_{\left\{ \int_{I_{j,k}} |\hat{f}_n - f_{j,\eta^k}|^2 \leq \delta^2 \right\}},$$

which yields

$$\begin{aligned} \mathbb{E}_{f_{j,\eta}}[Z(Y)] &\geq \delta^2 \mathbb{E}_{f_0, W} \left[\mathbb{E}_\tau (\Lambda_n(f_{j,\eta}, f_0)) \min \left(1, \frac{\mathbb{E}_\tau (\Lambda_n(f_{j,\eta^k}, f_0))}{\mathbb{E}_\tau (\Lambda_n(f_{j,\eta}, f_0))} \right) \right] \\ &= \delta^2 \mathbb{E}_{f_0} \left[\Lambda_n(f_{j,\eta}, f_0) \min \left(1, \frac{\mathbb{E}_\tau (\Lambda_n(f_{j,\eta^k}, f_0))}{\mathbb{E}_\tau (\Lambda_n(f_{j,\eta}, f_0))} \right) \right] \\ &= \delta^2 \mathbb{E}_{f_{j,\eta}} \left[\min \left(1, \frac{\mathbb{E}_\tau (\Lambda_n(f_{j,\eta^k}, f_0))}{\mathbb{E}_\tau (\Lambda_n(f_{j,\eta}, f_0))} \right) \right], \end{aligned}$$

and arguing as in the proof of Lemma 2.10 in [14] completes the proof. $\square$

Now remark that under the hypothesis $f = f_{j,\eta}$, then each Y_i is given by $dY_i(x) = f_{j,\eta}(x - \alpha_i)dx + dW_i(x)$ where each α_i is the true random shift of the i^{th} trajectory. Thus, under this hypothesis, we obtain $\mathbb{E}_\tau (\Lambda_n(f_{j,\eta}, f_0)) = \prod_{i=1}^n \int_{\mathbb{R}} g(\tau_i) e^{\left[\int_0^1 f_{j,\eta}(x - \tau_i) f_{j,\eta}(x - \alpha_i) dx + f_{j,\eta}(x - \tau_i) dW_i(x) - \frac{1}{2} \|f_{j,\eta}\|^2\right]} d\tau_i$, and $\mathbb{E}_\tau (\Lambda_n(f_{j,\eta^i}, f_0)) = \prod_{i=1}^n \int_{\mathbb{R}} g(\tau_i) e^{\left[\int_0^1 f_{j,\eta^i}(x - \tau_i) f_{j,\eta}(x - \alpha_i) dx + f_{j,\eta^i}(x - \tau_i) dW_i(x) - \frac{1}{2} \|f_{j,\eta^i}\|^2\right]} d\tau_i$. Using the two expressions above, we now study the condition (A.12).

Lemma A.4 *Following the choices of $j(n)$ and $\gamma_{j(n)}$ given in our algebraic setting, there exists $\lambda > 0$ and $\pi_0 > 0$ such that for all sufficiently large n*

$$\mathbb{P}_{f_{j,\eta}} \left(\frac{\mathbb{E}_\tau (\Lambda_n(f_{j,\eta^i}, f_0))}{\mathbb{E}_\tau (\Lambda_n(f_{j,\eta}, f_0))} \geq e^{-\lambda} \right) \geq \pi_0.$$

Proof of Lemma A.4 : to obtain the required bound, we use several second order Taylor expansions. From the Cauchy-Schwarz inequality, we have

$$\int_0^1 f_{j,\eta}(x - \tau_i) f_{j,\eta}(x - \alpha_i) dx = 1 + \int_0^1 f_{j,\eta}(x - \tau_i) f_{j,\eta}(x - \alpha_i) dx + \mathcal{O}_p(\|f_{j,\eta}\|^4)$$

A similar argument yields $\mathbb{E} \left[\left| \int_0^1 f_{j,\eta}(x - \tau_i) dW_i(x) \right| \right] \leq \|f_{j,\eta}\|$, and the Markov inequality used

with a second order expansion implies $e^{\int_0^1 f_{j,\eta}(x - \tau_i) dW_i(x)} = 1 + \int_0^1 f_{j,\eta}(x - \tau_i) dW_i(x) + \frac{1}{2} \left[\int_0^1 f_{j,\eta}(x - \tau_i) dW_i(x) \right]^2 + \mathcal{O}_p(\|f_{j,\eta}\|^3)$. Looking now at the complete expression of $\mathbb{E}_\tau (\Lambda_n(f_{j,\eta}, f_0))$, we obtain $\mathbb{E}_\tau (\Lambda_n(f_{j,\eta}, f_0)) = \prod_{i=1}^n \int_{\mathbb{R}} g(\tau_i) \left[1 + \int_0^1 f_{j,\eta}(x - \tau_i) f_{j,\eta}(x - \alpha_i) dx + \int_0^1 f_{j,\eta}(x - \tau_i) dW_i(x) + \frac{1}{2} \left[\int_0^1 f_{j,\eta}(x - \tau_i) dW_i(x) \right]^2 - \frac{1}{2} \|f_{j,\eta}\|^2 + \mathcal{O}_p(\|f_{j,\eta}\|^3) \right]$. The Fubini-type theorem for stochastic integrals (see for instance [15], chapter 3, lemma 4.1) enables to write $\log \mathbb{E}_\tau (\Lambda_n(f_{j,\eta}, f_0)) = \sum_{i=1}^n \log \left[1 + \int_0^1 (f_{j,\eta} \star g)(x) f_{j,\eta}(x - \alpha_i) dx + \int_0^1 (f_{j,\eta} \star g)(x) dW_i(x) \frac{1}{2} \int_{\mathbb{R}} \left[\int_0^1 f_{j,\eta}(x - \tau_i) dW_i(x) \right]^2 g(\tau_i) d\tau_i - \frac{1}{2} \|f_{j,\eta}\|^2 + \mathcal{O}_p(\|f_{j,\eta}\|^3) \right]$

Then, applying a classical expansion of the logarithm $\log(1 + z) = z - \frac{z^2}{2} + \mathcal{O}(z^3)$, we obtain

$$\log \mathbb{E}_\tau \Lambda_n(f_{j,\eta}, f_0) = z - \frac{z^2}{2} + \mathcal{O}_p(z^3) = \sum_{i=1}^n \int_0^1 (f_{j,\eta} \star g)(x) f_{j,\eta}(x - \alpha_i) dx + \int_0^1 (f_{j,\eta} \star g)(x) dW_i(x) \quad (\text{A.13})$$

$$+ \frac{1}{2} \sum_{i=1}^n \int_{\mathbb{R}} g(\tau_i) \left[\int_0^1 f_{j,\eta}(x - \tau_i) dW_i(x) \right]^2 - \frac{n}{2} \|f_{j,\eta}\|^2 \quad (\text{A.14})$$

$$- \frac{1}{2} \sum_{i=1}^n \left(\int_0^1 (f_{j,\eta} \star g)(x) f_{j,\eta}(x - \alpha_i) dx + \int_0^1 (f_{j,\eta} \star g)(x) dW_i(x) \right. \quad (\text{A.15})$$

$$\left. + \frac{1}{2} \int_{\mathbb{R}} g(\tau_i) \left[\int_0^1 f_{j,\eta}(x - \tau_i) dW_i(x) \right]^2 \right)^2 + \mathcal{O}_p(n \|f_{j,\eta}\|^3). \quad (\text{A.16})$$

We first discuss on the size of the terms in equations (A.15) and (A.16). The first term in (A.15) can be bounded using the Cauchy-Schwarz inequality

$$\sum_{i=1}^n \left(\int_0^1 (f_{j,\eta} \star g)(x) f_{j,\eta}(x - \alpha_i) dx \right)^2 \leq n \|f_{j,\eta} \star g\|^2 \|f_{j,\eta}\|^2 = \mathcal{O}_p(n \|f_{j,\eta}\|^4).$$

But observe that $\sum_{i=1}^n \mathbb{E}_{W_i} \left(\int_0^1 (f_{j,\eta} \star g)(x) dW_i(x) \right)^2 = n \|f_{j,\eta} \star g\|^2$ which does not converge to 0. Then, the Jensen inequality implies

$$\begin{aligned} & \sum_{i=1}^n \mathbb{E}_{W_i} \left(\int_{\mathbb{R}} g(\tau_i) \left[\int_0^1 f_{j,\eta}(x - \tau_i) dW_i(x) \right]^2 d\tau_i \right)^2 \\ & \leq \sum_{i=1}^n \int_{\mathbb{R}} g(\tau_i) \mathbb{E}_{W_i} \left[\int_0^1 f_{j,\eta}(x - \tau_i) dW_i(x) \right]^4 d\tau_i = \mathcal{O}_p(n \|f_{j,\eta}\|^4). \end{aligned}$$

Let us now study the terms derived from double products in equations (A.15) and (A.16), use first that $2|ab| \leq (a^2 + b^2)$ to get $\sum_{i=1}^n \mathbb{E}_{\alpha_i, W_i} \left| \int_0^1 (f_{j,\eta} \star g)(x) f_{j,\eta}(x - \alpha_i) dx \right| \left| \int_{\mathbb{R}} g(\tau_i) \left[\int_0^1 f_{j,\eta}(x - \tau_i) dW_i(x) \right]^2 d\tau_i \right| = \mathcal{O}_p(n \|f_{j,\eta}\|^4).$

The Cauchy-Schwarz and Jensen inequalities imply

$$\begin{aligned} & \sum_{i=1}^n \mathbb{E}_{W_i} \left| \int_0^1 (f_{j,\eta} \star g)(x) dW_i(x) \right| \left| \int_{\mathbb{R}} g(\tau_i) \left[\int_0^1 f_{j,\eta}(x - \tau_i) dW_i(x) \right]^2 d\tau_i \right| \\ & = \mathcal{O}_p(n \|f_{j,\eta}\|^3). \end{aligned}$$

At last, the Cauchy-Schwarz and Jensen inequalities on the remaining double-product term imply also

$$\begin{aligned} & \mathbb{E}_{W,\alpha} \left| \sum_{i=1}^n \int_0^1 (f_{j,\eta} \star g)(x) f_{j,\eta}(x - \alpha_i) dx \int_0^1 (f_{j,\eta} \star g)(x) dW_i(x) \right| \\ & = \mathcal{O}_p(n \|f_{j,\eta}\|^3). \end{aligned}$$

All the above bounds enables us to write

$$\begin{aligned} L_1 &:= \log \Lambda_n(f_{j,\eta}, f_0) \\ &= \sum_{i=1}^n \int_0^1 (f_{j,\eta} \star g)(x) f_{j,\eta}(x - \alpha_i) dx + \int_0^1 (f_{j,\eta} \star g)(x) dW_i(x) \\ &\quad + \frac{1}{2} \sum_{i=1}^n \int_{\mathbb{R}} g(\tau_i) \left[\int_0^1 f_{j,\eta}(x - \tau_i) dW_i(x) \right]^2 - \frac{n}{2} \|f_{j,\eta}\|^2 \\ &\quad - \frac{1}{2} \sum_{i=1}^n \left(\int_0^1 (f_{j,\eta} \star g)(x) dW_i(x) \right)^2 + \mathcal{O}_p(n \|f_{j,\eta}\|^3). \end{aligned}$$

In a similar way, we can also write

$$\begin{aligned} L_2 &:= \log \Lambda_n(f_{j,\eta^i}, f_0) = \sum_{i=1}^n \int_0^1 (f_{j,\eta^i} \star g)(x) f_{j,\eta}(x - \alpha_i) dx + \\ &\quad \int_0^1 (f_{j,\eta^i} \star g)(x) dW_i(x) + \frac{1}{2} \sum_{i=1}^n \int_{\mathbb{R}} g(\tau_i) \left[\int_0^1 f_{j,\eta^i}(x - \tau_i) dW_i(x) \right]^2 - \frac{n}{2} \|f_{j,\eta^i}\|^2 \\ &\quad - \frac{1}{2} \sum_{i=1}^n \left(\int_0^1 (f_{j,\eta^i} \star g)(x) dW_i(x) \right)^2 + \mathcal{O}_p(n \|f_{j,\eta}\|^3). \end{aligned}$$

For sake of simplicity, let us write $h = f_{j,\eta^i} - f_{j,\eta} = 2\eta_i\psi_{j,i}$. The difference $L = L_2 - L_1$ can thus be decomposed as

$$L = \sum_{i=1}^n \int_0^1 (h \star g)(x) [f_{j,\eta}(x - \alpha_i) - f_{j,\eta} \star g(x)] dx \quad (\text{A.17})$$

$$+ \sum_{i=1}^n \int_0^1 (h \star g)(x) (f_{j,\eta} \star g)(x) dx + \int_0^1 (h \star g)(x) dW_i(x) \quad (\text{A.18})$$

$$+ \frac{1}{2} \sum_{i=1}^n \int_{\mathbb{R}} g(\tau_i) \left[\int_0^1 f_{j,\eta^i}(x - \tau_i) dW_i(x) \right]^2 - \frac{n}{2} \|f_{j,\eta^i}\|^2 \quad (\text{A.19})$$

$$- \frac{1}{2} \sum_{i=1}^n \int_{\mathbb{R}} g(\tau_i) \left[\int_0^1 f_{j,\eta}(x - \tau_i) dW_i(x) \right]^2 + \frac{n}{2} \|f_{j,\eta}\|^2 \quad (\text{A.20})$$

$$- \frac{1}{2} \left[\sum_{i=1}^n \left(\int_0^1 (f_{j,\eta^i} \star g)(x) dW_i(x) \right)^2 - n \|f_{j,\eta^i} \star g\|^2 \right] \quad (\text{A.21})$$

$$- \frac{n}{2} \|f_{j,\eta^i} \star g\|^2 \quad (\text{A.22})$$

$$+ \frac{1}{2} \left[\sum_{i=1}^n \left(\int_0^1 (f_{j,\eta} \star g)(x) dW_i(x) \right)^2 - n \|f_{j,\eta} \star g\|^2 \right] \quad (\text{A.23})$$

$$+ \frac{n}{2} \|f_{j,\eta} \star g\|^2 \quad (\text{A.24})$$

$$+ \mathcal{O}_p(n \|f_{j,\eta}\|^3). \quad (\text{A.25})$$

Bound for (A.17) : we use the classical Bennett's inequality (see e.g [25]) for a sum of independent and bounded variables. Define $S = \sum_{i=1}^n \int_0^1 (h \star g)(x) [f_{j,\eta}(x - \alpha_i) - f_{j,\eta} \star g(x)] dx$. From Cauchy-Schwarz inequality, the random variables $\int_0^1 (h \star g)(x) f_{j,\eta}(x - \alpha_i) dx$ are bounded by a constant b such that $b = \|h \star g\| \|f_{j,\eta}\|$. Let v and c to be defined as

$$v = \sum_{i=1}^n \mathbb{E} \left[\int_0^1 (h \star g)(x) f_{j,\eta}(x - \alpha_i) dx \right]^2 \text{ and } c = b/3.$$

From the Cauchy Schwarz inequality, we have that $v \leq n \|f_{j,\eta}\|^2 \|h \star g\|^2$ and as $h = f_{j,\eta^i} - f_{j,\eta}$, by using our algebraic settings in Section A.2.1, we observe that $v \rightarrow 0$. The Bennett's inequality therefore implies that for any $\kappa > 0$:

$$\mathbb{P}(|S| \geq \kappa) \leq 2e^{\frac{-\kappa^2}{2(n\|f_{j,\eta}\|^2\|h \star g\|^2 + \kappa\|h \star g\|\|f_{j,\eta}\|/3)}}.$$

From our algebraic settings in Section A.2.1, one has thus that as $n \rightarrow \infty$, the $\mathbb{P}(|S| \geq \kappa)$ converges to 0.

Bound for (A.19,A.20,A.21,A.23) : applying Lemma A.5 (proved below) to the chi-square statistics in the expressions (A.19,A.20) yields that for any $\kappa > 0$ $\mathbb{P} \left(\left| \frac{1}{2} \sum_{i=1}^n \int_{\mathbb{R}} g(\tau_i) \left[\int_0^1 f_{j,\eta^i}(x - \tau_i) dW_i(x) \right]^2 - \frac{n}{2} \|f_{j,\eta^i}\|^2 \right| \geq \kappa \right) \leq 2e^{\frac{-\kappa^2}{n\|f_{j,\eta^i}\|^4 + 2\kappa\|f_{j,\eta^i}\|^2}}$. Similarly we obtain for the chi-square statistics in (A.21,A.23)

$$2e^{\frac{-\kappa^2}{n\|f_{j,\eta^i}\|^4 + 2\kappa\|f_{j,\eta^i}\|^2}}, \text{ and } \mathbb{P} \left(\left| \frac{1}{2} \sum_{i=1}^n \int_{\mathbb{R}} g(\tau_i) \left[\int_0^1 f_{j,\eta}(x - \tau_i) dW_i(x) \right]^2 - \frac{n}{2} \|f_{j,\eta}\|^2 \right| \geq \kappa \right) \leq 2e^{\frac{-\kappa^2}{n\|f_{j,\eta}\|^4 + 2\kappa\|f_{j,\eta}\|^2}}.$$

that for any $\kappa > 0$ $\mathbb{P} \left(\left| \frac{1}{2} \left[\sum_{i=1}^n \left(\int_0^1 (f_{j,\eta} \star g)(x) dW_i(x) \right)^2 - n \|f_{j,\eta} \star g\|^2 \right] \right| \geq \kappa \right) \leq 2e^{\frac{-\kappa^2}{n \|f_{j,\eta} \star g\|^4 + 2\kappa \|f_{j,\eta} \star g\|^2}},$
and
 $\mathbb{P} \left(\left| \frac{1}{2} \left[\sum_{i=1}^n \left(\int_0^1 (f_{j,\eta^i} \star g)(x) dW_i(x) \right)^2 - n \|f_{j,\eta^i} \star g\|^2 \right] \right| \geq \kappa \right)$
 $\leq 2e^{\frac{-\kappa^2}{n \|f_{j,\eta^i} \star g\|^4 + 2\kappa \|f_{j,\eta^i} \star g\|^2}}.$ It follows from the algebraic setting in Section A.2.1 that $n \|f_{j,\eta}\|^4 \rightarrow 0$ and $\|f_{j,\eta}\|^2 \rightarrow 0$, as well as $n \|f_{j,\eta} \star g\|^4 \rightarrow 0$ and $\|f_{j,\eta} \star g\|^2 \rightarrow 0$ and the above probabilities converge to zero as $n \rightarrow \infty$.

Bound for (A.18,A.22,A.24) : using the first term of (A.18), simple computation shows that yields $\sum_{i=1}^n \int_0^1 ((f_{j,\eta^i} - f_{j,\eta}) \star g)(x) (f_{j,\eta} \star g)(x) dx - \frac{n}{2} \|f_{j,\eta^i} \star g\|^2 + \frac{n}{2} \|f_{j,\eta} \star g\|^2 = -\frac{n}{2} \|h \star g\|^2$, and we obtain from our algebraic settings that this term converges to 0 since $n \|h \star g\|^2 \rightarrow 0$. Moreover, the second term of (A.18) is the sum of n i.i.d centered normal variables and the Cirelson-Ibragimov-Sudakov's inequality [7] ensures that

$$\mathbb{P} \left(\left| \sum_{i=1}^n \int_0^1 (h \star g)(x) dW_i(x) \right| \geq \kappa \right) \leq 2e^{\frac{-\kappa^2}{2n \|h \star g\|^2}},$$

and thus the above probability goes to zero.

Bound for (A.25): from our algebraic settings in Section A.2.1, it follows immediately that $n \|f_{j,\eta}\|^3 \rightarrow 0$.

Hence, by combining all the above bounds, it follows that we have shown that $L_2 - L_1$ is the sum of various terms which all converge to zero in probability or that are larger than some negative constant with probability tending to one as $n \rightarrow +\infty$, which completes the proof of Lemma A.4. $\square$

Lemma A.5 *Let g be a density function on $\mathbb{R}$, and $(W_i)_{i \in \{1 \dots n\}}$ be independent standard Brownian motions on $[0, 1]$. Then, for any $f \in L^2([0, 1])$ and $\alpha > 0$,*

$$P \left(\frac{1}{2} \sum_{i=1}^n \int_{\mathbb{R}} g(\tau_i) \left[\int_0^1 f(t - \tau_i) dW_i(t) \right]^2 d\tau_i - \frac{n}{2} \|f\|^2 \geq \alpha \right) \leq e^{\frac{-\alpha^2}{n \|f\|^4 + 2\alpha \|f\|^2}}.$$

Proof of Lemma A.5 Consider $\zeta_n = \frac{1}{2} \sum_{i=1}^n \int_{\mathbb{R}} g(\tau_i) \left[\int_0^1 f(t - \tau_i) dW_i(t) \right]^2 d\tau_i - \frac{n}{2} \|f\|^2$. We use a Laplace transform technique to bound $\mathbb{P}(\zeta_n \geq \alpha)$. For any $\frac{1}{\|f\|^2} > t > 0$, we have by Markov's inequality

$$\mathbb{P}(\zeta_n \geq \alpha) \leq e^{-\alpha t - \frac{n}{2} \|f\|^2 t} \prod_{i=1}^n \mathbb{E} \left[e^{\frac{t}{2} \int_{\mathbb{R}} g(\tau_i) \left(\int_0^1 f(t - \tau_i) dW_i(t) \right)^2 d\tau_i} \right].$$

We apply now Jensen's inequality for the exponential function and the measure $g(\tau) d\tau$ to obtain

$$\mathbb{P}(\zeta_n \geq \alpha) \leq e^{-\alpha t - \frac{n}{2} \|f\|^2 t} \prod_{i=1}^n \int_{\mathbb{R}} g(\tau_i) \mathbb{E} \left[e^{\frac{t}{2} \left(\int_0^1 f(t - \tau_i) dW_i(t) \right)^2} \right] d\tau_i.$$

Remark that $\left(\int_0^1 f(t - \tau_i) dW_i(t)\right)^2$ follows a chi-square distribution whose Laplace transform does not depend on τ_i and thus

$$\mathbb{P}(\zeta_n \geq \alpha) \leq e^{-\alpha t - \frac{n}{2}\|f\|^2 t - \frac{n}{2} \log(1 - t\|f\|^2)}.$$

Let $\tilde{\alpha} = \frac{\alpha}{n/2\|f\|^2}$ and minimizing now the last bound with respect to t yield the optimal choice $t^* = \frac{\tilde{\alpha}}{1+\tilde{\alpha}}$. With this choice, we obtain $\mathbb{P}(\zeta_n \geq \alpha) \leq \exp(\frac{n}{2} [\log(1 + \tilde{\alpha}) - \tilde{\alpha}])$. Now use the classical bound $\log(1 + u) - u \leq \frac{-u^2}{2(1+u)}$, valid for all $u \geq 0$, to get $\mathbb{P}(\zeta_n \geq \alpha) \leq \exp(\frac{n}{2} \times \frac{\tilde{\alpha}^2}{2(1+\tilde{\alpha})}) = \exp(\frac{-\alpha^2}{n\|f\|^4 + 2\alpha\|f\|^2})$, which completes the proof of the lemma. $\square$

A.2.4 A lower bound for the minimax risk

By Lemma A.3 and Lemma A.4, it follows that there exists a constant C_1 such that for all sufficiently large n ,

$$\inf_{\hat{f}_n} \sup_{f \in B_{p,q}^s(A)} \mathbb{E} \left\| \hat{f}_n - f \right\|^2 \geq \inf_{\hat{f}_n} \max_{\eta \in \{\pm 1\}^{2j}} \mathbb{E}_{f_{j,\eta}} \left\| \hat{f}_n - f_{j,\eta} \right\|^2 \geq C_1 n^{-\frac{2s}{2s+2\nu+1}},$$

which completes the proof of Theorem 4.1. $\square$

Acknowledgements

We would like to thank Patrick Cattiaux for fruitful discussions on likelihood ratios and the Girsanov formula.

References

- [1] ALLASSONNIÈRE, S., AMIT, Y. AND TROUVÉ, A. (2007). *Toward a coherent statistical framework for dense deformable template estimation*, Journal of the Royal Statistical Society (B), 69, 3–29.
- [2] BIGOT, J. (2006). *Landmark-based registration of curves via the continuous wavelet transform*, Journal of Computational and Graphical Statistics, 15 (3), 542–564.
- [3] BIGOT, J., GADAT, S AND LOUBES, J.M. (2007). *Statistical M-Estimation and Consistency in large deformable models for Image Warping*, Journal of Mathematical Imaging and Vision, to be published.
- [4] BIGOT, J. , GAMBOA, F. AND VIMOND, M. (2008). *Estimation of translation, rotation and scaling between noisy images using the Fourier Mellin transform*, SIAM Journal on Imaging Sciences, to be published.
- [5] BUCKHEIT, J.B. , CHEN, S. , DONOHO, D.L. AND JOHNSTONE, I. (1995). *Wavelab reference manual*, Department of Statistics, Stanford University, <http://www-stat.stanford.edu/software/wavelab>.
- [6] CAVALIER, L. , GOLUBEV, G. K. , PICARD, D. AND TSYBAKOV, A. B. (2002). *Oracle inequalities for inverse problems*, The Annals of Statistics, 30 (3), 843–874.
- [7] CIRELSON, B. S. , IBRAGIMOV, I. A. AND SUDAKOV, V. N. (1976). *Norms of Gaussian sample functions*, Lecture Notes in Mathematics, Berlin: Springer-Verlag, 550, 20–41.

- [8] DONOHO, D. L. (1995). *Nonlinear solution of linear inverse problems by wavelet-vaguelette decomposition*, Appl. Comput. Harmon. Anal., 2 (2), 101–126.
- [9] DONOHO, D. L. , JOHNSTONE, I. M. , KERKYACHARIAN, G. AND PICARD, D. (1995). *Wavelet Shrinkage: Asymptopia?*, Journal of the Royal Statistical Society (B), 57, 301–369.
- [10] GASSER, T. AND KNEIP, A. (1995). *Searching for Structure in Curve Samples*, Journal of the American Statistical Association, 90 (432), 1179–1188.
- [11] GASSER, T. AND KNEIP, A. (1992). *Statistical Tools to Analyze Data Representing a Sample of Curves*, The Annals of Statistics, 20 (3), 1266–1305.
- [12] GLASBEY, C. A. AND MARDIA, K. V. (2001). *A penalized likelihood approach to image warping* (with discussion), Journal of the Royal Statistical Society (B), 63 (3), 465–514.
- [13] GRENANDER, U. (1993). *General Pattern Theory: A Mathematical Study of Regular Structures*, Oxford University Press, New York.
- [14] HARDLE, W., KERKYACHARIAN, G., PICARD, D. AND TSYBAKOV, A. (1998). *Wavelets, Approximation and. Statistical Applications*, Lecture Notes in Statistics, New York: Springer-Verlag.
- [15] IKEDA, N. AND WATANABE, S (1989). *Stochastic Differential Equations and Diffusion Processes*, Second Edition, North-Holland/Kodansya, Tokyo.
- [16] ISSERLES, U., RITOV, Y. AND TRIGANO, T. (2008). *Semiparametric density estimation of shifts between curves*, Technical Report.
- [17] JOHNSTONE, I. , KERKYACHARIAN, G. , PICARD, D. AND RAIMONDO, M. (2004). *Wavelet deconvolution in a periodic setting*, Journal of the Royal Statistical Society (B), 66, 547–573.
- [18] KNEIP, A. AND GASSER, T. (1988). *Convergence and consistency results for self-modelling regression*, The Annals of Statistics, 16, 82–112.
- [19] KOLACZYK, E.D. (1994). *Wavelet Methods for the Inversion of Certain Homogeneous Linear Operators in the Presence of Noisy Data*, Ph.D. thesis, Department of Statistics, Stanford University.
- [20] KOROSTEL'EV, A. P. AND TSYBAKOV, A. B. (1993). *Minimax theory of image reconstruction*, , Lecture Notes in Statistics, New York.
- [21] LIU, X. AND MÜLLER, H.G. (2004). *Functional Convex Averaging and Synchronization for Time-Warped Random Curves*, Journal of the American Statistical Association, 99 (467), 687–699.
- [22] LOUBES, J.M., MAZA, E. AND GAMBOA, F. (2007). *Semi-parametric estimation of shifts*, Electronic Journal of Statistics, 1, 616–640.
- [23] MA, J. , MILLER M.I., TROUVÉ A. AND YOUNES L. (2008). *Bayesian template estimation in computational anatomy*, NeuroImage, 42 (1), 252–261.
- [24] MALLAT, S. (1998). *A Wavelet Tour of Signal Processing*, Academic Press, New York.
- [25] MASSART, P. (2006). *Concentration Inequalities and Model Selection: Ecole d'été de Probabilités de Saint-Flour XXXIII - 2003*, Lecture Notes in Mathematics Springer.
- [26] MEYER, Y. (1992). *Wavelets and operators*, Cambridge Studies in Advanced Mathematics, Cambridge University Press.

- [27] PENSKEY, M. AND SAPATINAS, T. (2008). *Functional deconvolution in a periodic setting: uniform case*, The Annals of Statistics, to be published.
- [28] PENSKEY, M. AND VIDAKOVIC, B. (1999). *Adaptive Wavelet Estimator for Nonparametric Density Deconvolution*, The Annals of Statistics, 27, 2033–2053.
- [29] RAIMONDO, M. AND STEWART, M. (2007). *The WaveD Transform in R: performs fast translation-invariant wavelet deconvolution*, Journal of Statistical Software, 21 (3), 1-27.
- [30] RAMSAY, J.O. AND LI, X. (2001). *Curve Registration*, Journal of the Royal Statistical Society (B), 63, 243-259.
- [31] RONN, B. (1998). *Nonparametric Maximum Likelihood Estimation for Shifted Curves*, Journal of the Royal Statistical Society (B), 60, 351-363.
- [32] ROSENTHAL, H. P. (1972). *On the span in L_p of sequences of independent random variables. II, Proceedings of the Sixth Berkeley Symposium on Mathematical Statistics and Probability (Univ. California, Berkeley, Calif., 1970/1971), Vol. II: Probability theory, 149–167.*
- [33] VIMOND, M. (2008). *Efficient estimation for homothetic shifted regression models*, The Annals of Statistics, to be published.
- [34] WANG, K. AND GASSER, T. (1997). *Alignment of Curves by Dynamic Time Warping*, The Annals of Statistics, 25 (3), 1251-1276.
- [35] WILLER, T. (2006). *Deconvolution in white noise with a random blurring function*, Technical report.